LM36010 具有 1.5A 高侧电流源的同步升压、单 LED 闪光灯驱动器

1 特性

- 精确且可编程 LED 电流
  - 闪光灯/IR 电流范围：11mA 至 1.5A（128 个级别）
  - 手电筒电流范围：2.4mA 至 376mA（128 个级别）
- 闪光灯超时时间长达 1.6 秒
- 优化了低电池电量条件下的闪光灯 LED 电流 (IVFM)
- LED 阴极对地短路运行以提高热管理
- 较小的总体解决方案尺寸：< 7mm^2
- 硬件闪光灯使能 (STROBE)
- 输入电压范围：2.5V 至 5.5V
- 400kHz I^{2}C 兼容接口
  - I^{2}C 地址 = 0x64

2 应用

- 手机
- 平板电脑
- IR LED 驱动器
- 视频监控：IP 摄像机
- 条形码扫描仪
- 便携式数据终端

3 说明

LM36010 是一款超小型 LED 闪光灯驱动器，具有高度可调节性。总解决方案尺寸为 7mm^2，可提供高达 1.5A 的 LED 闪光灯电流或高达 376mA 的手电筒电流。

该器件采用 2MHz 或 4MHz 固定频率的同步升压转换器为 1.5A 恒定电流 LED 源供电。自适应调节方法可在闪光灯模式下将电流控制在 11mA 至 1.5A 的范围内，或在手电筒模式下将电流控制在 2.4mA 至 376mA 的范围内，因此可确保电流源保持可调节状态，并可最大限度地提高效率。

LM36010 的特性由与 I^{2}C 兼容的接口控制。这些 特性包括：硬件闪光灯 (STROBE) 以及适用于闪光灯和影片模式（手电筒）的 128 级可编程电流。该器件的开关频率为 2MHz 或 4MHz，具备过压保护 (OVP) 和可调节限流功能，因此可使用微型超薄电感器和陶瓷电容器。该器件可在 -40°C 至 +85°C 的环境温度范围下工作。

器件信息(1)

器件型号	封装	封装尺寸（标称值）
LM36010	DSBGA (8)	1.512mm × 0.800mm

(1) 要了解所有可用封装，请参阅数据表末尾的可订购产品附录。

简化电路原理图



Copyright © 2016, Texas Instruments Incorporated

An IMPORTANT NOTICE at the end of this data sheet addresses availability, warranty, changes, use in safety-critical applications, intellectual property matters and other important disclaimers. PRODUCTION DATA.

目录

1 特性 ... 1
2 应用 ... 1
3 说明 ... 1
4 修订历史记录 ... 2
5 **Pin Configuration and Functions** ... 3
6 **Specifications** ... 4
6.1 Absolute Maximum Ratings ... 4
6.2 ESD Ratings ... 4
6.3 Recommended Operating Conditions ... 4
6.4 Thermal Information ... 4
6.5 Electrical Characteristics ... 5
6.6 Timing Requirements ... 5
6.7 Switching Characteristics ... 5
6.8 Typical Characteristics ... 7
7 **Detailed Description** ... 12
7.1 Overview ... 12
7.2 Functional Block Diagram ... 13
7.3 Feature Description ... 14
7.4 Device Functioning Modes ... 16
7.5 Programming ... 18
7.6 Register Descriptions ... 20
8 **Applications and Implementation** ... 22
8.1 Application Information ... 22
8.2 Typical Application ... 22
9 **Power Supply Recommendations** ... 33
10 **Layout** ... 33
10.1 Layout Guidelines ... 33
10.2 Layout Example ... 34
11 器件和文档支持 ... 35
11.1 器件支持 ... 35
11.2 文档支持 ... 35
11.3 接收文档更新通知 ... 35
11.4 社区资源 ... 35
11.5 商标 ... 35
11.6 静电放电警告 ... 35
11.7 Glossary ... 35
12 机械、封装和可订购信息 ... 36

4 修订历史记录

Changes from Revision A (July 2017) to Revision B	Page
• 更正了封装尺寸	36

Changes from Original (April 2017) to Revision A	Page
• 已更改 器件状态从“高级信息”更改为“生产数据”	1

Copyright © 2017, Texas Instruments Incorporated

5 Pin Configuration and Functions

YKB Package
8-Pin DSBGA
Top View



Pin Functions

PIN		TYPE(1)	DESCRIPTION
NAME	NO.		
A1	GND	G	Ground
A2	IN	P	Input voltage connection. Connect IN to the input supply and bypass to GND with a 10-µF or larger ceramic capacitor.
B1	SW	P	Drain connection for Internal NMOS and synchronous PMOS switches.
B2	STROBE	I	Active high hardware flash enable. Drive STROBE high to turn on flash pulse. An internal pulldown resistor of 300 kΩ is between STROBE and GND.
C1	OUT	P	Step-up DC-DC converter output. Connect a 10-µF ceramic capacitor between this terminal and GND.
C2	SDA	I/O	I^2C serial data input/output.
D1	LED	P	High-side current source output for flash LED.
D2	SCL	I	I^2C serial clock input.

(1) G = Ground; P = Power; I = Input; O = Output

Copyright © 2017, Texas Instruments Incorporated

6 Specifications

6.1 Absolute Maximum Ratings

over operating free-air temperature range (unless otherwise noted)[1][2]

	MIN	MAX	UNIT
IN, SW, OUT, LED	−0.3	6	V
SDA, SCL, STROBE	−0.3	(V_{IN}+ 0.3) w/ 6 V maximum	
Continuous power dissipation[3]	Internally limited		
Junction temperature, T_{J-MAX}		150	°C
Storage temperature, T_{stg}	−65	150	°C

(1) Stresses beyond those listed under *Absolute Maximum Ratings* may cause permanent damage to the device. These are stress ratings only, which do not imply functional operation of the device at these or any other conditions beyond those indicated under *Recommended Operating Conditions*. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.
(2) All voltages are with respect to the potential at the GND pin.
(3) Internal thermal shutdown circuitry protects the device from permanent damage. Thermal shutdown engages at T_J = 150°C (typical) and disengages at T_J = 135°C (typical). Thermal shutdown is ensured by design.

6.2 ESD Ratings

			VALUE	UNIT
$V_{(ESD)}$	Electrostatic discharge	Human-body model (HBM), per ANSI/ESDA/JEDEC JS-001[1]	±1000	V
		Charged-device model (CDM), per JEDEC specification JESD22-C101[2]	±250	

(1) JEDEC document JEP155 states that 500-V HBM allows safe manufacturing with a standard ESD control process.
(2) JEDEC document JEP157 states that 250-V CDM allows safe manufacturing with a standard ESD control process.

6.3 Recommended Operating Conditions

over operating free-air temperature range (unless otherwise noted)[1][2]

		MIN	MAX	UNIT
V_{IN}		2.5	5.5	V
Junction temperature, T_J		−40	125	°C
Ambient temperature, T_A [3]		−40	85	°C

(1) Stresses beyond those listed under *absolute maximum ratings* may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under *recommended operating conditions* is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.
(2) All voltages are with respect to the potential at the GND pin.
(3) In applications where high power dissipation and/or poor package thermal resistance is present, the maximum ambient temperature may have to be derated. Maximum ambient temperature (T_{A-MAX}) is dependent on the maximum operating junction temperature ($T_{J-MAX-OP}$ = 125°C), the maximum power dissipation of the device in the application (P_{D-MAX}), and the junction-to-ambient thermal resistance of the part/package in the application ($R_{\theta JA}$), as given by the following equation: $T_{A-MAX} = T_{J-MAX-OP} – (R_{\theta JA} \times P_{D-MAX})$.

6.4 Thermal Information

THERMAL METRIC[1]		LM36010 YKB (DSBGA) 8 PINS	UNIT
$R_{\theta JA}$	Junction-to-ambient thermal resistance	117.3	°C/W
$R_{\theta JC(top)}$	Junction-to-case (top) thermal resistance	1.3	°C/W
$R_{\theta JB}$	Junction-to-board thermal resistance	34.3	°C/W
Ψ_{JT}	Junction-to-top characterization parameter	0.5	°C/W
Ψ_{JB}	Junction-to-board characterization parameter	34.6	°C/W

(1) For more information about traditional and new thermal metrics, see the *Semiconductor and IC Package Thermal Metrics* application report.

Copyright © 2017, Texas Instruments Incorporated

6.5 Electrical Characteristics

T_A = 25°C and V_{IN} = 3.6 V, unless otherwise specified. Minimum and maximum limits apply over the full operating ambient temperature range (–40°C ≤ TA ≤ 85°C).(1)(2)

PARAMETER		TEST CONDITIONS		MIN	TYP	MAX	UNIT
CURRENT SOURCE SPECIFICATIONS							
I_{LED}	Current source accuracy	V_{OUT} = 4 V , flash code = 0x7F = 1.5 A (3)		–10%	1.5	10%	A
		V_{OUT} = 4 V , torch code = 0x7F = 376 mA		–10%	376	10%	mA
V_{HR}	LED current source regulation voltage	I_{LED} = 1.5 A	Flash		550		mV
		I_{LED} = 376 mA	Torch		350		
V_{OVP}	Overvoltage Protection	ON threshold		4.86	5	5.10	V
		OFF threshold		4.71	4.85	4.95	
STEP-UP DC-DC CONVERTER SPECIFICATIONS							
R_{PMOS}	PMOS switch on-resistance				175		mΩ
R_{NMOS}	NMOS switch on-resistance				130		
I_{CL}	Switch current limit	Reg 0x01, bit [5] = 0		–15%	1.9	15%	A
		Reg 0x01, bit [5] = 1		–15%	2.8	15%	
V_{UVLO}	Undervoltage lockout threshold	Falling V_{IN}			2.5		V
V_{IVFM}	Input voltage flash monitor trip threshold	Reg 0x02, bits [7:5] = 000		–3%	2.9	3%	V
I_Q	Quiescent supply current	Device not switching, in pass mode			0.3		mA
I_{SB}	Standby supply current	Device disabled 2.5 V ≤ V_{IN} ≤ 5.5 V			0.8	4	µA
STROBE VOLTAGE SPECIFICATIONS							
V_{IL}	Input logic low	2.5 V ≤ V_{IN} ≤ 5.5 V		0		0.4	V
V_{IH}	Input logic high			1.2		V_{IN}	V
I^2C-COMPATIBLE INTERFACE SPECIFICATIONS (SCL, SDA)							
V_{IL}	Input logic low	2.5 V ≤ V_{IN} ≤ 4.2 V		0		0.4	V
V_{IH}	Input logic high			1.2		V_{IN}	
V_{OL}	Output logic low	I_{LOAD} = 3 mA				400	mV

(1) Minimum (MIN) and Maximum (MAX) limits are specified by design, test, or statistical analysis. Typical (TYP) numbers are not verified, but do represent the most likely norm. Unless otherwise specified, conditions for typical specifications are: V_{IN} = 3.6 V and T_A = 25°C.
(2) All voltages are with respect to the potential at the GND pin.
(3) The ability to deliver 1.5 A of LED current is highly dependent upon the input voltage, LED voltage, ambient temperature and PCB layout. Depending upon the system conditions, it is possible that the device could hit the internal thermal shutdown or thermal scale-back value before the desired flash duration is reached. See Thermal Performance for more details.

6.6 Timing Requirements

		MIN	NOM	MAX	UNIT
t_1	SCL clock period	2.4			µs
t_2	Data in set-up time to SCL high	100			ns
t_3	Data out stable after SCL low	0			ns
t_4	SDA low set-up time to SCL low (start)	100			ns
t_5	SDA high hold time after SCL high (stop)	100			ns

6.7 Switching Characteristics

over operating free-air temperature range (unless otherwise noted)

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
f_{SW}	Switching frequency	2.5 V ≤ V_{IN} ≤ 5.5 V	-10%	2	10%	MHz
			-10%	4	10%	



图 1. I²C-Compatible Interface Specifications

版权 © 2017, Texas Instruments Incorporated

6.8 Typical Characteristics

T_A = 25°C, V_{IN} = 3.6 V, C_{IN} = 10 µF, C_{OUT} = 10 µF, L = 1 µH, V_{LED} = 3.4 V, Flash Time-out = 320 ms and Thermal Scale-Back (TSB) disabled, unless otherwise noted.



f_{SW} = 2 MHz I_{CL} = 2.8 A

图 2. LED Flash Current vs Brightness Code



f_{SW} = 4 MHz I_{CL} = 2.8 A

图 3. LED Flash Current vs Brightness Code



f_{SW} = 2 MHz I_{CL} = 2.8 A

图 4. LED Flash Current vs Input Voltage



f_{SW} = 2 MHz I_{CL} = 2.8 A

图 5. LED Flash Current vs Input Voltage



f_{SW} = 2 MHz I_{FLASH} = 1.5 A
I_{CL} = 1.9 A Flash Time-out < 120 ms at 85°C

图 6. LED Flash Current vs Input Voltage



f_{SW} = 4 MHz I_{FLASH} = 1.5 A
I_{CL} = 1.9 A Flash Time-out < 120 ms at 85°C

图 7. LED Flash Current vs Input Voltage

Typical Characteristics (接下页)

T_A = 25°C, V_{IN} = 3.6 V, C_{IN} = 10 µF, C_{OUT} = 10 µF, L = 1 µH, V_{LED} = 3.4 V, Flash Time-out = 320 ms and Thermal Scale-Back (TSB) disabled, unless otherwise noted.



图 8. LED Flash Current vs Input Voltage



图 9. LED Flash Current vs Input Voltage



图 10. LED Flash Current vs Input Voltage



图 11. LED Flash Current vs Input Voltage



图 12. LED Flash Current vs Input Voltage



图 13. LED Flash Current vs Input Voltage

版权 © 2017, Texas Instruments Incorporated

Typical Characteristics (接下页)

T_A = 25°C, V_{IN} = 3.6 V, C_{IN} = 10 µF, C_{OUT} = 10 µF, L = 1 µH, V_{LED} = 3.4 V, Flash Time-out = 320 ms and Thermal Scale-Back (TSB) disabled, unless otherwise noted.



f_{SW} = 2 MHz I_{FLASH} = 0.75 A I_{CL} = 1.9 A

图 14. LED Flash Current vs Input Voltage



f_{SW} = 4 MHz I_{FLASH} = 0.75 A I_{CL} = 1.9 A

图 15. LED Flash Current vs Input Voltage



f_{SW} = 2 MHz I_{FLASH} = 0.75 A I_{CL} = 2.8 A

图 16. LED Flash Current vs Input Voltage



f_{SW} = 4 MHz I_{FLASH} = 0.75 A I_{CL} = 2.8 A

图 17. LED Flash Current vs Input Voltage



f_{SW} = 2 MHz

图 18. LED Torch Current vs Brightness Code



f_{SW} = 4 MHz

图 19. LED Torch Current vs Brightness Code

Typical Characteristics (接下页)

T_A = 25°C, V_{IN} = 3.6 V, C_{IN} = 10 µF, C_{OUT} = 10 µF, L = 1 µH, V_{LED} = 3.4 V, Flash Time-out = 320 ms and Thermal Scale-Back (TSB) disabled, unless otherwise noted.



f_{SW} = 2 MHz

图 20. LED Torch Current vs Input Voltage



f_{SW} = 2 MHz

图 21. LED Torch Current vs Input Voltage



f_{SW} = 2 MHz I_{TORCH} = 376 mA

图 22. LED Torch Current vs Input Voltage



f_{SW} = 4 MHz I_{TORCH} = 376 mA

图 23. LED Torch Current vs Input Voltage



f_{SW} = 2 MHz I_{TORCH} = 258 mA

图 24. LED Torch Current vs Input Voltage



f_{SW} = 2 MHz I_{TORCH} = 188 mA

图 25. LED Torch Current vs Input Voltage

版权 © 2017, Texas Instruments Incorporated

Typical Characteristics (接下页)

T_A = 25°C, V_{IN} = 3.6 V, C_{IN} = 10 µF, C_{OUT} = 10 µF, L = 1 µH, V_{LED} = 3.4 V, Flash Time-out = 320 ms and Thermal Scale-Back (TSB) disabled, unless otherwise noted.



Mode (Reg 0x01 bits[1:0]) = 01 (IR Mode)

图 26. LED Off Current vs Input Voltage



Mode (Reg 0x01 bits[1:0]) = 10 (Torch Mode)

图 27. LED On Current vs Input Voltage



图 28. Standby Current vs Input Voltage

7 Detailed Description

7.1 Overview

The LM36010 is a high-power white LED flash driver capable of delivering up to 1.5 A to the LED. The device incorporates a 2-MHz or 4-MHz constant frequency-synchronous current-mode PWM boost converter and a high-side current source to regulate the LED current over the 2.5-V to 5.5-V input voltage range.

The LM36010 PWM DC-DC boost converter switches and boosts the output to maintain at least V_{HR} across the current source. This minimum headroom voltage ensures that the current source remains in regulation. If the input voltage is above the LED voltage + current source headroom voltage the device does not switch, but turns the PFET on continuously (pass mode). In pass mode, the drop across the current source is the difference between (V_{IN} - I_{LED} × R_{PMOS}) and V_{LED}.

The device has one logic input for a hardware flash enable (STROBE). This logic input has an internal 300-kΩ (typical) pulldown resistor to GND.

Additional features of the device include an input voltage monitor that can reduce the flash current during low V_{IN} conditions and a temperature based current scale-back feature that forces the flash current to the set torch level if the on-chip junction temperature reaches 125°C.

Control is done via an I^2C-compatible interface. This includes adjustment of the flash and torch current levels, changing the switch current limit, and changing the flash time-out duration. Additionally, there are flag and status bits that indicate flash current time-out, LED over-temperature condition, LED failure (open/short), device thermal shutdown, thermal current scale-back, and V_{IN} undervoltage conditions.

版权 © 2017, Texas Instruments Incorporated

7.2 Functional Block Diagram



Copyright © 2017, Texas Instruments Incorporated

7.3 Feature Description

7.3.1 Flash Mode

In flash mode, the LED current source provides 128 target current levels from 11 mA to 1.5 A, set by the LED Flash Brightness Register (0x03 bits [6:0]). Flash mode is activated by the Enable Register (0x01), setting mode M1, M0 (bits [1:0]) to 11. Once the flash sequence is activated, the LED current source ramps up to the programmed flash current by stepping through all current steps until the programmed current is reached. The headroom on the current source is regulated to provide 11 mA to 1.5 A.

When flash mode is enabled using the mode M1, M0 (bits [1:0]) of the Enable Register (0x01), the mode bits in the Enable Register are cleared after a flash time-out event.

7.3.2 Torch Mode

In torch mode, the LED current source provides 128 target current levels from 2.4 mA to 376 mA, set by the LED Torch Brightness Register (0x04 bits [6:0]). Torch mode is activated by the Enable Register (0x01), setting mode M1, M0 (bits [1:0]) to 10. Once the TORCH sequence is activated, the LED current source ramps up to the programmed torch current by stepping through all current steps until the programmed current is reached. The rate at which the current ramps is determined by the value chosen in the Torch Ramp bit [0] in Timing Register (0x02).

7.3.3 IR Mode

In IR mode, the target LED current is equal to the value stored in the LED Flash Brightness Register (0x03 bits [7:0]). When IR mode is enabled by the Enable Register (0x01) setting mode M1, M0 (bits [1:0]) to 01, the boost converter turns on and sets the output equal to the input (pass mode). In IR mode, toggling the STROBE pin enables and disables the LED current source. The STROBE pin can only be set to be Level sensitive, as all timing of the IR pulse is externally controlled. In IR mode, the current source does not control the ramp rate of the LED output. The current transitions immediately from off to on and then on to off.



(1) If needed, the DC/DC boost will turn on when the LED current is delivered (Strobe Pin = High). When the Strobe Pin goes low, the output voltage will return to V_{IN} (Pass Mode)

图 29. IR Mode with Boost

版权 © 2017, Texas Instruments Incorporated

Feature Description (接下页)



(1) In pass mode, the boost stays disabled and $V_{OUT} = V_{IN}$ when the Strobe Pin is high or low

图 30. IR Mode Pass Only



(1) When the flash timer elapses, the device goes into stand-by regardless of strobe state

图 31. IR Mode Time-out

7.4 Device Functioning Modes

7.4.1 Start-Up (Enabling The Device)

At turnon the LED current source steps through each FLASH or TORCH level until the target LED current is reached. This gives the device a controlled turnon and limits inrush current from the V_{IN} supply. The target LED flash and the target LED torch currents are set by the LED Flash Brightness Register (0x03 bits [6:0]) and LED Torch Brightness Register (0x04 bits [6:0]) respectively.

7.4.2 Pass Mode

The LM36010 starts up in pass mode and stays there until boost mode is needed to maintain regulation. If the voltage difference between V_{OUT} and V_{LED} falls below V_{HR}, the device switches to boost mode. In pass mode, the boost converter does not switch, the synchronous PFET turns fully on bringing V_{OUT} up to $V_{IN} – I_{LED} × R_{PMOS}$, and the inductor current is not limited by the peak current limit.

7.4.3 Input Voltage Flash Monitor (IVFM)

The LM36010 has the ability to adjust the flash current based upon the voltage level present at the IN pin utilizing the input voltage flash monitor (IVFM). The adjustable threshold IVFM-D ranges from 2.9 V to 3.6 V in 100-mV steps and is set by Configuration Register (0x02) bits [7:5]. Additionally, the IVFM-D threshold sets the input voltage boundary that forces the LM36010 to stop ramping the flash current during start-up.



图 32. IVFM Mode

7.4.4 Fault/Protections

Upon a fault condition, the LM36010 sets the appropriate flag(s) in the Flags Register (0x05) and switches into stand-by mode obtained by clearing the mode M1, M0 (bits [1:0]) of the Enable Register (0x01). The LM36010 remains in standby until an I^2C read of the Flags Register. I^2C read of the Flags Register clears the flags and the fault status can be re-checked. If the fault(s) is still present, the LM36010 re-sets the appropriate flag bits and enters stand-by again.

7.4.4.1 Overvoltage Protection (OVP)

The output voltage is limited to typically 5 V (see V_{OVP} specification in the *Electrical Characteristics*). In situations such as an open LED, the LM36010 raises the output voltage in order to keep the LED current at its target value. When V_{OUT} reaches 5 V (typical), the overvoltage comparator trips and turns off the internal NFET. When OVP condition is present for three consecutive OVP events, LM36010 enters stand-by mode and OVP flag (bit [0]) of Flags Register (0x01) is set. Checking for three consecutive events prevents forcing the device to shut down due to momentary OVP condition. When V_{OUT} falls below the V_{OVP} off threshold, the LM36010 switches again.

版权 © 2017, Texas Instruments Incorporated

Device Functioning Modes (接下页)

7.4.4.2 Input Voltage Flash Monitor (IVFM)

When the input voltage crosses the IVFM-D value, programmed by Configuration Register (0x02) bits [7:5], the LM36010 sets the IVFM flag (bit [6]) of Flags Register (0x05).

7.4.4.3 LED and/or VOUT Short Fault

LM36010 enters stand-by mode from flash or torch mode and V_{LED} Short Fault flag (bit [5]) of Flags Register (0x05) is set, if the LED output and/or VOUT experiences a short condition. An LED short condition occurs if the voltage at the LED pin goes below 500 mV (typical). There is a deglitch time of 256 µs before the LED short flag is valid, and a deglitch time of 2.048 ms before the VOUT short flag is valid. The LED and/or VOUT short fault can be reset to 0 by removing power to the LM36010, or setting the software reset field (Register 0x06 bit [7]) to a 1, or by reading back the Flags Register.

7.4.4.4 Current Limit (OCP)

The LM36010 features two selectable inductor current limits, 1.9A and 2.8A, programmable through the I^2C-compatible interface by writing to Register 0x01 bit [5] . When the inductor current limit is reached, the LM36010 terminates the charging phase of the switching cycle and sets the OCP flag (bit [4]) of Flags Register (0x05). However, the mode M1, M0 (bits [1:0]) are not cleared as the device operates at current limit. Switching resumes at the start of the next switching period.

In pass mode, there is no mechanism to limit the current as the current does not flow through the NMOS, which senses the current limit.

In the boost mode or the pass mode, if V_{OUT} falls below 2.3 V, the device stops switching, and the PFET operates as a current source limiting the current to 200 mA. This prevents the LM36010 from drawing excessive current from the battery during output short-circuit conditions.

7.4.4.5 Thermal Scale-Back (TSB)

When the LM36010 die temperature reaches 125°C, the thermal scale-back (TSB) circuit trips and TSB flag (bit [2]) of Flags Register (0x05) is set. The LED current then shifts to torch current level, set by the LED Torch Brightness Register (0x04 bits [6:0]) for the duration of the flash pulse, set by the flash time-out in the Configuration Register (0x02 bits [4:1]) After I^2C read of the Flags Register and upon re-flash, if the die temperature is still above 125°C, the LM36010 re-enters into torch current level and sets the TSB flag bit again.

7.4.4.6 Thermal Shutdown (TSD)

When the LM36010 die temperature reaches 150°C, the thermal shutdown (TSD) circuit trips, forcing the LM36010 into standby and writing a 1 to the TSD flag (bit [2]) of the Flags Register (0x05). The LM36010 restarts only after the Flags Register is read, which clears the fault flag. Upon restart, if the die temperature is still above 150°C, the LM36010 resets the TSD flag and re-enters standby.

7.4.4.7 Undervoltage Lockout (UVLO)

The LM36010 has an internal comparator that monitors the voltage at IN pin. If the input voltage drops to 2.5 V, the UVLO flag (bit [1]) of Flags Register (0x05) is set and the LM36010 switches to stand-by mode. After the UVLO flag is set, even if the input voltage rises above 2.5 V, the LM36010 is not available for operation until there is an I^2C read of the Flags Register. Upon an I^2C read of the Flags Register, the UVLO fault is cleared and normal operation can resume.

7.4.4.8 Flash Time-out (FTO)

The LM36010 sources the flash current for the time period set by Flash Time-out (0x02 bits [4:1]). The LED current source has 16 time-out levels ranging from 40 ms to 1600 ms.

7.5 Programming

7.5.1 Control Truth Table

M1 (Register 0x01 bit[1])	M0 (Register 0x01 bit[0])	STROBE EN (Register 0x01 bit[2])	STROBE PIN	ACTION
0	0	0	X	Standby
0	0	1	pos edge	Ext flash
1	0	X	X	Int torch
1	1	X	X	Int flash
0	1	0	X	IR LED standby
0	1	1	0	IR LED standby
0	1	1	pos edge	IR LED enabled

7.5.2 I^2C-Compatible Interface

7.5.2.1 Data Validity

The data on SDA must be stable during the HIGH period of the clock signal (SCL). In other words, the state of the data line can only be changed when SCL is LOW.



图 33. Data Validity Data

A pullup resistor between the VIO line of the controller and SDA must be greater than [**(VIO – V_{OL}) / 3 mA**] to meet the V_{OL} requirement on SDA. Using a larger pullup resistor results in lower switching current with slower edges, while using a smaller pullup resistor results in higher switching currents with faster edges.

7.5.2.2 Start and Stop Conditions

START and STOP conditions classify the beginning and the end of the I^2C session. A START condition is defined as the SDA signal transitioning from HIGH to LOW while SCL line is HIGH. A STOP condition is defined as the SDA transitioning from LOW to HIGH while SCL is HIGH. The I^2C master always generates START and STOP conditions. The I^2C bus is considered busy after a START condition and free after a STOP condition. During data transmission, the I^2C master can generate repeated START conditions. First START and repeated START conditions are equivalent, function-wise.



图 34. Start and Stop Conditions

版权 © 2017, Texas Instruments Incorporated

7.5.2.3 Transferring Data

Every byte put on the SDA line must be eight bits long, with the most significant bit (MSB) transferred first. Each byte of data has to be followed by an acknowledge bit. The acknowledge related clock pulse is generated by the master. The master releases the SDA line (HIGH) during the acknowledge clock pulse. The LM36010 pulls down the SDA line during the 9th clock pulse, signifying an acknowledge. The LM36010 generates an acknowledge after each byte is received. There is no acknowledge created after data is read from the device.

After the START condition, the I^2C master sends a chip address. This address is seven bits long followed by an eighth bit which is a data direction bit (R/W). The LM36010 7-bit address is 0x64. For the eighth bit, a 0 indicates a WRITE, and a 1 indicates a READ. The second byte selects the register to which the data is written. The third byte contains data to write to the selected register.



图 35. Write Cycle W = Write (SDA = 0) R = Read (SDA = 1) Ack = Acknowledge (SDA Pulled Down by Either Master or Slave) ID = Chip Address, 64h for LM36010

7.5.2.4 I^2C-Compatible Chip Address

The device address for the LM36010 is 1100100 (0x64). After the START condition, the I^2C-compatible master sends the 7-bit address followed by an eighth read or write bit (R/W). R/W = 0 indicates a WRITE and R/W = 1 indicates a READ. The second byte following the device address selects the register address to which the data is written. The third byte contains the data for the selected register.



图 36. I^2C-Compatible Chip Address

7.6 Register Descriptions

REGISTER NAME	INTERNAL HEX ADDRESS	POWER ON/RESET VALUE
		LM36010
Enable Register	0x01	0x20
Configuration Register	0x02	0x15
LED Flash Brightness Register	0x03	0x00
LED Torch Brightness Register	0x04	0x00
Flags Register	0x05	0x00
Device ID Register	0x06	0x01

7.6.1 Enable Register (0x01)

Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0
Boost Mode 0 = Normal (Default) 1 = Pass Mode Only	**Boost Frequency Select** 0 = 2 MHz (Default) 1 = 4 MHz	**Boost Current Limit Setting** 0 = 1.9 A 1 = 2.8 A (Default)	**IVFM Enable** 0 = Disabled (Default) 1 = Enabled	**Strobe Type** 0 = Level Triggered (Default) 1 = Edge Triggered	**Strobe Enable** 0 = Disabled (Default) 1 = Enabled	**Mode Bits: M1, M0** 00 = Standby (Default) 01 = IR Drive 10 = Torch 11 = Flash	

注

Edge strobe mode is not valid in IR MODE. Switching between level and edge strobe types while the device is enabled is not recommended.

In edge or level strobe mode, TI recommends that the trigger pulse width be set greater than 1 ms to ensure proper turn-on of the device.

7.6.2 Configuration Register (0x02)

Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0
IVFM Levels (IVFM-D) 000 = 2.9 V (Default) 001 = 3 V 010 = 3.1 V 011 = 3.2 V 100 = 3.3 V 101 = 3.4 V 110 = 3.5 V 111 = 3.6 V			**Flash Time-out Duration** 0000 = 40 ms 0001 = 80 ms 0010 = 120 ms 0011 = 160 ms 0100 = 200 ms 0101 = 240 ms 0110 = 280 ms 0111 = 320 ms 1000 = 360 ms 1001 = 400 ms 1010 = 600 ms (Default) 1011 = 800 ms 1100 = 1000 ms 1101 = 1200 ms 1110 = 1400 ms 1111 = 1600 ms				**Torch Ramp** 0 = No Ramp 1 = 1 ms (default)

注

On the LM36010, special care must be taken with regards to thermal management when using time-out values greater than 500 ms. Depending on the PCB layout, input voltage, and output current, it is possible to have the internal thermal shutdown circuit trip prior to reaching the desired flash time-out value.

版权 © 2017, Texas Instruments Incorporated

7.6.3 LED Flash Brightness Register (0x03)

Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0
Thermal Current Scale-Back 0 = Disabled 1 = Enabled (default) If enabled, the LED current shifts to torch current level if T_J reaches 125 °C	**LED Flash Brightness Level** 0000000 = 11 mA (Default) ..... 00010101 (0x15) = 0.257 A ..... 0111111 (0x3F) = 0.75 A ..... 0101111 (0x5F) = 1.03 A ..... 01100110 (0x66) = 1.2 A ..... 1111111 (0x7F) = 1.5 A						

7.6.4 LED Torch Brightness Register (0x04)

Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0
RFU	**LED Torch Brightness Levels** 0000000 = 2.4 mA (Default) ..... 00010101 (0x15) = 64 mA ..... 0111111 (0x3F) = 188 mA ..... 0101111 (0x5F) = 258 mA ..... 01100110 (0x66) = 302 mA ..... 1111111 (0x7F) = 376 mA						

7.6.5 Flags Register (0x05)

Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0
OVP Fault	**IVFM Trip Flag**	**V_{OUT} / V_{LED} Short Fault**	**Current Limit Flag**	**Thermal Current Scale-back (TSB) Flag**	**Thermal Shutdown (TSD) Fault**	**UVLO Fault**	**Flash Time-Out Flag**

7.6.6 Device ID and RESET Register (0x06)

Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0
Software RESET 0 = Normal (default) 1 = Force device RESET	**RFU**	**Device ID** 000			**Silicon Revision Bits** 001		

8 Applications and Implementation

注

Information in the following applications sections is not part of the TI component specification, and TI does not warrant its accuracy or completeness. TI's customers are responsible for determining suitability of components for their purposes. Customers should validate and test their design implementation to confirm system functionality.

8.1 Application Information

The LM36010 can drive a flash LED at currents up to 1.5 A. The 2-MHz or 4-MHz DC-DC boost regulator allows for the use of small value discrete external components.

8.2 Typical Application



Copyright © 2016, Texas Instruments Incorporated

图 37. LM36010 Typical Application

8.2.1 Design Requirements

Example requirements based on default register values:

表 1. Design Parameters

DESIGN PARAMETER	EXAMPLE VALUE
Input voltage range	2.5 V to 5.5 V
Brightness control	I^2C Register
LED configuration	1 flash LED
Boost switching frequency	2 MHz (4 MHz selectable)
Flash brightness	1.5-A maximum current

版权 © 2017, Texas Instruments Incorporated

8.2.2 Detailed Design Procedure

8.2.2.1 Thermal Performance

Output power is limited by three things: the peak current limit, the ambient temperature, and the maximum power dissipation in the package. If the die temperature of the device is below the absolute maximum rating of 125°C, the maximum output power can be over 6 W. However, any appreciable output current causes the internal power dissipation to increase and therefore increase the die temperature. Any circuit configuration must ensure that the die temperature remains below 125°C taking into account the ambient temperature derating. The thermal scale-back protection (TSB) helps ensure that temperature requirement is held valid. If the TSB feature is disabled, thermal shutdown (TSD) is the next level of protection for the device, which is set to 150°C. This mechanism cannot be disabled, and operation of the device above 125°C is not ensured by the electrical specification.

In boost mode, where $V_{IN} < V_{LED} + V_{HR}$, the power dissipation can be approximated by 公式 1:

$$P_{DISS} \approx \left[\left[\left(\frac{(V_{OUT} - V_{IN}) \times V_{OUT}}{V_{IN}^2}\right) \times I_{LED}^2 \times R_{NFET}\right] + \left[\left(\frac{V_{OUT}}{V_{IN}}\right) \times I_{LED}^2 \times R_{PFET}\right] + (V_{HR} \times I_{LED})\right] \tag{1}$$

When the device is in pass mode, where $V_{IN} > V_{LED} + V_{HR}$, the power dissipation equals:

$$P_{DISS} = \left[\left[(V_{IN} - V_{LED}) \times I_{LED}\right] - \left(I_{LED}^2 \times R_{INDUCTOR}\right)\right] \tag{2}$$

Use 公式 3 to calculate the junction temperature (T_J) of the device:

$$T_J = R_{\theta JA} \times P_{DISS} \tag{3}$$

Note that these equations only provide approximation of the junction temperature and do not take into account thermal time constants, which play a large role in determining maximum deliverable output power and flash durations.

8.2.2.2 Output Capacitor Selection

The LM36010 is designed to operate with a 10-µF ceramic output capacitor. When the boost converter is running, the output capacitor supplies the load current during the boost converter on-time. When the NMOS switch turns off, the inductor energy is discharged through the internal PMOS switch, supplying power to the load and restoring charge to the output capacitor. This causes a sag in the output voltage during the on-time and a rise in the output voltage during the off-time. Therefore, choose the output capacitor to limit the output ripple to an acceptable level depending on load current and input or output voltage differentials and also to ensure the converter remains stable.

Larger capacitors such as a 22-µF or capacitors in parallel can be used if lower output voltage ripple is desired. To estimate the output voltage ripple considering the ripple due to capacitor discharge (ΔV_Q) and the ripple due to the capacitors ESR (ΔV_{ESR}), use 公式 4 and 公式 5:

For continuous conduction mode, the output voltage ripple due to the capacitor discharge is:

$$\Delta V_Q = \frac{I_{LED} \times (V_{OUT} - V_{IN})}{f_{SW} \times V_{OUT} \times C_{OUT}} \tag{4}$$

The output voltage ripple due to the output capacitors ESR is found by:

$$\Delta V_{ESR} = R_{ESR} \times \left(\left(\frac{I_{LED} \times V_{OUT}}{V_{IN}}\right) + \Delta_{IL}\right) \Delta I_L = \frac{V_{IN} \times (V_{OUT} - V_{IN})}{2 \times f_{SW} \times L \times V_{OUT}} \tag{5}$$

In ceramic capacitors, the ESR is very low so the assumption is that 80% of the output voltage ripple is due to capacitor discharge and 20% from ESR. 表 2 lists different manufacturers for various output capacitors and their case sizes suitable for use with the LM36010.

8.2.2.3 Input Capacitor Selection

Choosing the correct size and type of input capacitor helps minimize the voltage ripple caused by the switching of the boost converter and reduces noise on the input pin of the boost converter that can feed through and disrupt internal analog signals. In the typical application circuit a 10-µF ceramic input capacitor works well. It is important to place the input capacitor as close as possible to the LM36010 input (IN) pin. This reduces the series resistance and inductance that can inject noise into the device due to the input switching currents. 表 2 lists various input capacitors recommended for use with the LM36010.

表 2. Recommended Input/Output Capacitors (X5R/X7R Dielectric)

MANUFACTURER	PART NUMBER	VALUE	CASE SIZE	VOLTAGE RATING
TDK Corporation	C1608JB0J106M	10 µF	0603 (1.6 mm × 0.8 mm × 0.8 mm)	6.3 V
TDK Corporation	C2012JB1A106M	10 µF	0805 (2 mm × 1.25 mm × 1.25 mm)	10 V
Murata	GRM188R60J106M	10 µF	0603 (1.6 mm × 0.8 mm × 0.8 mm)	6.3 V
Murata	GRM21BR61A106KE19	10 µF	0805 (2 mm × 1.25 mm × 1.25 mm)	10 V

8.2.2.4 Inductor Selection

The LM36010 is designed to use a 0.47-µH or 1-µH inductor. 表 3 lists various inductors and their manufacturers that work well with the LM36010. When the device is boosting ($V_{OUT} > V_{IN}$) the inductor is typically the largest area of efficiency loss in the circuit. Therefore, choosing an inductor with the lowest possible series resistance is important. Additionally, the saturation rating of the inductor must be greater than the maximum operating peak current of the LM36010. This prevents excess efficiency loss that can occur with inductors that operate in saturation. For proper inductor operation and circuit performance, ensure that the inductor saturation and the peak current limit setting of the LM36010 are greater than I_{PEAK} in 公式 6:

$$I_{PEAK} = \frac{I_{LED}}{\eta} \times \frac{V_{OUT}}{V_{IN}} + \Delta I_L \Delta I_L = \frac{V_{IN} \times (V_{OUT} - V_{IN})}{2 \times f_{SW} \times L \times V_{OUT}}$$

where

- f_{SW} = 2 or 4 MHz (6)

Efficiency details can be found in the *Application Curves*.

表 3. Recommended Inductors

MANUFACTURER	L	PART NUMBER	DIMENSIONS (L×W×H)	I_{SAT}	R_{DC}
TOKO	0.47 µH	DFE201610P-R470M	2 mm × 1.6 mm × 1 mm	4.1 A	32 mΩ
TOKO	1 µH	DFE201610P-1R0M	2 mm × 1.6 mm × 1 mm	3.7 A	58 mΩ

版权 © 2017, Texas Instruments Incorporated

8.2.3 Application Curves

T_A = 25°C, V_{IN} = 3.6 V, C_{IN} = 10 µF, C_{OUT} = 10 µF, L = 1 µH, V_{LED} = 3.4 V, Flash Time-out = 320 ms and Thermal Scale-Back (TSB) disabled, unless otherwise noted.



f_{SW} = 2 MHz I_{CL} = 2.8 A

图 38. LED Flash Efficiency vs Brightness Code



f_{SW} = 4 MHz I_{CL} = 2.8 A

图 39. LED Flash Efficiency vs Brightness Code



f_{SW} = 2 MHz I_{CL} = 2.8 A

图 40. LED Flash Efficiency vs Input Voltage



f_{SW} = 2 MHz I_{CL} = 2.8 A

图 41. LED Flash Efficiency vs Input Voltage



f_{SW} = 2 MHz I_{FLASH} = 1.5 A
I_{CL} = 1.9 A Flash Time-out < 120 ms at 85°C

图 42. LED Flash Efficiency vs Input Voltage



f_{SW} = 4 MHz I_{FLASH} = 1.5 A
I_{CL} = 1.9 A Flash Time-out < 120 ms at 85°C

图 43. LED Flash Efficiency vs Input Voltage

T_A = 25°C, V_{IN} = 3.6 V, C_{IN} = 10 µF, C_{OUT} = 10 µF, L = 1 µH, V_{LED} = 3.4 V, Flash Time-out = 320 ms and Thermal Scale-Back (TSB) disabled, unless otherwise noted.



f_{SW} = 2 MHz　　I_{FLASH} = 1.2 A
I_{CL} = 1.9 A　　Flash Time-out < 280 ms at 85°C

图 44. LED Flash Efficiency vs Input Voltage



f_{SW} = 4 MHz　　I_{FLASH} = 1.2 A
I_{CL} = 1.9 A　　Flash Time-out < 280 ms at 85°C

图 45. LED Flash Efficiency vs Input Voltage



f_{SW} = 2 MHz　　I_{FLASH} = 1.03 A　　I_{CL} = 1.9 A

图 46. LED Flash Efficiency vs Input Voltage



f_{SW} = 4 MHz　　I_{FLASH} = 1.03 A　　I_{CL} = 1.9 A

图 47. LED Flash Efficiency vs Input Voltage



f_{SW} = 2 MHz　　I_{FLASH} = 1.03 A　　I_{CL} = 2.8 A

图 48. LED Flash Efficiency vs Input Voltage



f_{SW} = 4 MHz　　I_{FLASH} = 1.03 A　　I_{CL} = 2.8 A

图 49. LED Flash Efficiency vs Input Voltage

版权 © 2017, Texas Instruments Incorporated

T_A = 25°C, V_{IN} = 3.6 V, C_{IN} = 10 µF, C_{OUT} = 10 µF, L = 1 µH, V_{LED} = 3.4 V, Flash Time-out = 320 ms and Thermal Scale-Back (TSB) disabled, unless otherwise noted.



f_{SW} = 2 MHz I_{FLASH} = 0.75 A I_{CL} = 1.9 A

图 50. LED Flash Efficiency vs Input Voltage



f_{SW} = 4 MHz I_{FLASH} = 0.75 A I_{CL} = 1.9 A

图 51. LED Flash Efficiency vs Input Voltage



f_{SW} = 2 MHz I_{FLASH} = 0.75 A I_{CL} = 2.8 A

图 52. LED Flash Efficiency vs Input Voltage



f_{SW} = 4 MHz I_{FLASH} = 0.75 A I_{CL} = 2.8 A

图 53. LED Flash Efficiency vs Input Voltage



f_{SW} = 2 MHz

图 54. LED Torch Efficiency vs Brightness Code



f_{SW} = 4 MHz

图 55. LED Torch Efficiency vs Brightness Code

T_A = 25°C, V_{IN} = 3.6 V, C_{IN} = 10 µF, C_{OUT} = 10 µF, L = 1 µH, V_{LED} = 3.4 V, Flash Time-out = 320 ms and Thermal Scale-Back (TSB) disabled, unless otherwise noted.



f_{SW} = 2 MHz

图 56. LED Torch Efficiency vs Input Voltage



f_{SW} = 2 MHz

图 57. LED Torch Efficiency vs Input Voltage



f_{SW} = 2 MHz I_{TORCH} = 376 mA

图 58. LED Torch Efficiency vs Input Voltage



f_{SW} = 4 MHz I_{TORCH} = 376 mA

图 59. LED Torch Efficiency vs Input Voltage



f_{SW} = 2 MHz I_{TORCH} = 258 mA

图 60. LED Torch Efficiency vs Input Voltage



f_{SW} = 2 MHz I_{TORCH} = 188 mA

图 61. LED Torch Efficiency vs Input Voltage

版权 © 2017, Texas Instruments Incorporated

T_A = 25°C, V_{IN} = 3.6 V, C_{IN} = 10 µF, C_{OUT} = 10 µF, L = 1 µH, V_{LED} = 3.4 V, Flash Time-out = 320 ms and Thermal Scale-Back (TSB) disabled, unless otherwise noted.



Time (400 µs/DIV)
Mode bits (Reg 0x01 bit[1:0]) = 11 (Flash Mode)

图 62. Flash Start-up with I²C



Time (100 ms/DIV)
Flash Time-out (Reg 0x02 bits[4:1]) = 0111 (320 ms)

图 63. Flash Time-Out



Time (2 ms/DIV)

图 64. Flash Turnoff with I²C



Time (400 µs/DIV)
Mode bits (Reg 0x01 bit[1:0]) = 10 (Torch Mode)

图 65. Torch Start-up with I²C



Time (4 ms/DIV)
Mode bits (Reg 0x01 bit[1:0]) = 00 (Standby Mode)

图 66. Torch Turnoff with I²C



Time (400 µs/DIV)
STROBE Enabled (Reg 0x01 bit[2] = 1)

图 67. Flash Start-up with STROBE

T_A = 25°C, V_{IN} = 3.6 V, C_{IN} = 10 µF, C_{OUT} = 10 µF, L = 1 µH, V_{LED} = 3.4 V, Flash Time-out = 320 ms and Thermal Scale-Back (TSB) disabled, unless otherwise noted.



Time (100 ms/DIV)
STROBE Enabled (Reg 0x01 bit[2] = 1)
Level Triggered (Reg 0x01 bit[3] = 0)
Strobe pulse = 100 ms

图 68. Flash Turnoff with Level Triggered STROBE



Time (100 ms/DIV)
STROBE Enabled (Reg 0x01 bit[2] = 1)
Edge Triggered (Reg 0x01 bit[3] = 1)
Flash Time-out = 320 ms

图 69. Flash Turnoff with Edge Triggered STROBE



Time (400 µs/DIV)
Reg 0x01 = 0x26

图 70. Boost I²C Torch



Time (400 µs/DIV)
Reg 0x01 = 0x27

图 71. Boost I²C Flash



Time (400 µs/DIV)
Reg 0x01 = 0x2C

图 72. Boost Edge Triggered Flash



Time (400 µs/DIV)
Reg 0x01 = 0x24

图 73. Boost Level Triggered Flash

版权 © 2017, Texas Instruments Incorporated

T_A = 25°C, V_{IN} = 3.6 V, C_{IN} = 10 µF, C_{OUT} = 10 µF, L = 1 µH, V_{LED} = 3.4 V, Flash Time-out = 320 ms and Thermal Scale-Back (TSB) disabled, unless otherwise noted.



Time (400 µs/DIV)
Reg 0x01 = 0xA6

图 74. Pass Mode I²C Torch



Time (400 µs/DIV)
Reg 0x01 = 0xA7

图 75. Pass Mode I²C Flash



Time (400 µs/DIV)
Reg 0x01 = 0xAC

图 76. Pass mode Edge Triggered Flash



Time (400 µs/DIV)
Reg 0x01 = 0xA4

图 77. Pass mode Level Triggered Flash



Time (200 ns/DIV)
f_{SW} = 2 MHz

图 78. Inductor Current and Switch node (SW) Waveform



Time (200 ns/DIV)
f_{SW} = 4 MHz

图 79. Inductor Current and Switch node (SW) Waveform

T_A = 25°C, V_{IN} = 3.6 V, C_{IN} = 10 µF, C_{OUT} = 10 µF, L = 1 µH, V_{LED} = 3.4 V, Flash Time-out = 320 ms and Thermal Scale-Back (TSB) disabled, unless otherwise noted.



Time (400 µs/DIV)

Reg 0x01 = 0x13

IVFM Trip Level (Reg 0x02 bits[7:5]) = 001 (3 V)

图 80. IVFM - Ramp and Hold

版权 © 2017, Texas Instruments Incorporated

9 Power Supply Recommendations

The LM36010 is designed to operate from an input voltage supply range between 2.5 V and 5.5 V. This input supply must be well regulated and capable to supply the required input current. If the input supply is located far from the LM36010 additional bulk capacitance may be required in addition to the ceramic bypass capacitors.

10 Layout

10.1 Layout Guidelines

The high switching frequency and large switching currents of the LM36010 make the choice of layout important. The following steps are to be used as a reference to ensure the device is stable and maintains proper LED current regulation across its intended operating voltage and current range.

1. Place C_{IN} on the top layer (same layer as the LM36010) and as close as possible to the device. The input capacitor conducts the driver currents during the low-side MOSFET turnon and turnoff and can detect current spikes over 1 A in amplitude. Connecting the input capacitor through short, wide traces to both the IN and GND pins reduces the inductive voltage spikes that occur during switching which can corrupt the V_{IN} line.
2. Place C_{OUT} on the top layer (same layer as the LM36010) and as close as possible to the OUT and GND pins. The returns for both C_{IN} and C_{OUT} must come together at one point, as close as possible to the GND pin. Connecting C_{OUT} through short, wide traces reduce the series inductance on the OUT and GND pins that can corrupt the V_{OUT} and GND lines and cause excessive noise in the device and surrounding circuitry.
3. Connect the inductor on the top layer close to the SW pin. There must be a low-impedance connection from the inductor to SW due to the large DC inductor current, and at the same time the area occupied by the SW node must be small so as to reduce the capacitive coupling of the high dV/dT present at SW that can couple into nearby traces.
4. Avoid routing logic traces near the SW node so as to avoid any capacitively coupled voltages from SW onto any high-impedance logic lines such as STROBE, SDA, and SCL. A good approach is to insert an inner layer GND plane underneath the SW node and between any nearby routed traces. This creates a shield from the electric field generated at SW.
5. Terminate the flash LED cathode directly to the GND pin of the LM36010. If possible, route the LED return with a dedicated path so as to keep the high amplitude LED current out of the GND plane. For a flash LED that is routed relatively far away from the LM36010, a good approach is to sandwich the forward and return current paths over the top of each other on two layers. This helps reduce the inductance of the LED current path.

10.2 Layout Example



图 81. LM36010 Layout Example

版权 © 2017, Texas Instruments Incorporated

11 器件和文档支持

11.1 器件支持

11.1.1 Third-Party Products Disclaimer

TI'S PUBLICATION OF INFORMATION REGARDING THIRD-PARTY PRODUCTS OR SERVICES DOES NOT CONSTITUTE AN ENDORSEMENT REGARDING THE SUITABILITY OF SUCH PRODUCTS OR SERVICES OR A WARRANTY, REPRESENTATION OR ENDORSEMENT OF SUCH PRODUCTS OR SERVICES, EITHER ALONE OR IN COMBINATION WITH ANY TI PRODUCT OR SERVICE.

11.2 文档支持

11.2.1 相关文档

相关文档如下：

AN-1112 DSBGA 晶圆级芯片级封装

11.3 接收文档更新通知

要接收文档更新通知，请转至 TI.com 上的器件产品文件夹。单击右上角的*通知我* 进行注册，即可每周接收产品信息更改摘要。有关更改的详细信息，请查看任何已修订文档中包含的修订历史记录。

11.4 社区资源

下列链接提供到 TI 社区资源的连接。链接的内容由各个分销商“按照原样”提供。这些内容并不构成 TI 技术规范，并且不一定反映 TI 的观点；请参阅 TI 的 《使用条款》。

TI E2E™ 在线社区 ***TI 的工程师对工程师 (E2E) 社区。***此社区的创建目的在于促进工程师之间的协作。在 e2e.ti.com 中，您可以咨询问题、分享知识、拓展思路并与同行工程师一道帮助解决问题。

设计支持 ***TI 参考设计支持*** 可帮助您快速查找有帮助的 E2E 论坛、设计支持工具以及技术支持的联系信息。

11.5 商标

E2E is a trademark of Texas Instruments.
All other trademarks are the property of their respective owners.

11.6 静电放电警告

ESD 可能会损坏该集成电路。德州仪器 (TI) 建议通过适当的预防措施处理所有集成电路。如果不遵守正确的处理措施和安装程序，可能会损坏集成电路。

ESD 的损坏小至导致微小的性能降级，大至整个器件故障。 精密的集成电路可能更容易受到损坏，这是因为非常细微的参数更改都可能会导致器件与其发布的规格不相符。

11.7 Glossary

SLYZ022 — *TI Glossary*.

This glossary lists and explains terms, acronyms, and definitions.

12 机械、封装和可订购信息

以下页面包含机械、封装和可订购信息。这些信息是指定器件的最新可用数据。这些数据如有变更，恕不另行通知和修订此文档。如欲获取此产品说明书的浏览器版本，请参阅左侧的导航。

YKB0008

PACKAGE OUTLINE

DSBGA - 0.5 mm max height

DIE SIZE BALL GRID ARRAY



NOTES:

1. All linear dimensions are in millimeters. Any dimensions in parenthesis are for reference only. Dimensioning and tolerancing per ASME Y14.5M.
2. This drawing is subject to change without notice.

版权 © 2017, Texas Instruments Incorporated

EXAMPLE BOARD LAYOUT

YKB0008 — **DSBGA - 0.5 mm max height**

DIE SIZE BALL GRID ARRAY



LAND PATTERN EXAMPLE
SCALE:40X



SOLDER MASK DETAILS
NOT TO SCALE

4223222/A 08/2016

NOTES: (continued)

3. Final dimensions may vary due to manufacturing tolerance considerations and also routing constraints. For more information, see Texas Instruments literature number SNVA009 (www.ti.com/lit/snva009).

EXAMPLE STENCIL DESIGN

YKB0008 DSBGA - 0.5 mm max height

DIE SIZE BALL GRID ARRAY



SOLDER PASTE EXAMPLE
BASED ON 0.075 - 0.1 mm THICK STENCIL
SCALE:40X

4223222/A 08/2016

NOTES: (continued)

4. Laser cutting apertures with trapezoidal walls and rounded corners may offer better paste release.

版权 © 2017, Texas Instruments Incorporated

PACKAGING INFORMATION

Orderable part number	Status (1)	Material type (2)	Package | Pins	Package qty | Carrier	RoHS (3)	Lead finish/ Ball material (4)	MSL rating/ Peak reflow (5)	Op temp (°C)	Part marking (6)
LM36010YKBR	Active	Production	DSBGA (YKB) | 8	3000 | LARGE T&R	Yes	SNAGCU	Level-1-260C-UNLIM	-40 to 85	6010
LM36010YKBR.A	Active	Production	DSBGA (YKB) | 8	3000 | LARGE T&R	Yes	SNAGCU	Level-1-260C-UNLIM	-40 to 85	6010

(1) **Status:** For more details on status, see our product life cycle.

(2) **Material type:** When designated, preproduction parts are prototypes/experimental devices, and are not yet approved or released for full production. Testing and final process, including without limitation quality assurance, reliability performance testing, and/or process qualification, may not yet be complete, and this item is subject to further changes or possible discontinuation. If available for ordering, purchases will be subject to an additional waiver at checkout, and are intended for early internal evaluation purposes only. These items are sold without warranties of any kind.

(3) **RoHS values:** Yes, No, RoHS Exempt. See the TI RoHS Statement for additional information and value definition.

(4) **Lead finish/Ball material:** Parts may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

(5) **MSL rating/Peak reflow:** The moisture sensitivity level ratings and peak solder (reflow) temperatures. In the event that a part has multiple moisture sensitivity ratings, only the lowest level per JEDEC standards is shown. Refer to the shipping label for the actual reflow temperature that will be used to mount the part to the printed circuit board.

(6) **Part marking:** There may be an additional marking, which relates to the logo, the lot trace code information, or the environmental category of the part.

Multiple part markings will be inside parentheses. Only one part marking contained in parentheses and separated by a "~" will appear on a part. If a line is indented then it is a continuation of the previous line and the two combined represent the entire part marking for that device.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

重要通知和免责声明

TI“按原样”提供技术和可靠性数据（包括数据表）、设计资源（包括参考设计）、应用或其他设计建议、网络工具、安全信息和其他资源，不保证没有瑕疵且不做出任何明示或暗示的担保，包括但不限于对适销性、与某特定用途的适用性或不侵犯任何第三方知识产权的暗示担保。

这些资源可供使用 TI 产品进行设计的熟练开发人员使用。您将自行承担以下全部责任：(1) 针对您的应用选择合适的 TI 产品，(2) 设计、验证并测试您的应用，(3) 确保您的应用满足相应标准以及任何其他安全、安保法规或其他要求。

这些资源如有变更，恕不另行通知。TI 授权您仅可将这些资源用于研发本资源所述的 TI 产品的相关应用。严禁以其他方式对这些资源进行复制或展示。您无权使用任何其他 TI 知识产权或任何第三方知识产权。对于因您对这些资源的使用而对 TI 及其代表造成的任何索赔、损害、成本、损失和债务，您将全额赔偿，TI 对此概不负责。

TI 提供的产品受 TI 销售条款)、TI 通用质量指南 或 ti.com 上其他适用条款或 TI 产品随附的其他适用条款的约束。TI 提供这些资源并不会扩展或以其他方式更改 TI 针对 TI 产品发布的适用的担保或担保免责声明。 除非德州仪器 (TI) 明确将某产品指定为定制产品或客户特定产品，否则其产品均为按确定价格收入目录的标准通用器件。

TI 反对并拒绝您可能提出的任何其他或不同的条款。

版权所有 © 2025，德州仪器 (TI) 公司

最后更新日期：2025 年 10 月