





Support & training



SN74LV393B-EP ZHCSSV8 - AUGUST 2023

# SN74LV393B-EP 增强型产品 2V 至 5.5V 低噪声双路 4 位二进制计数器

# 1 特性

- 2V 至 5.5V V<sub>CC</sub> 运行 •
- 所有端口上均支持以混合模式电压运行 ٠
- loff 支持局部断电模式运行
- 闩锁性能超过 250mA, 符合 JESD 17 规范
- 工作环境温度:-55°C 至 +125°C
- 支持国防、航空航天和医疗应用:
  - 受控基线
  - 一个组装和测试基地
  - 一个制造基地
  - 延长了产品生命周期
  - 产品可追溯性

## 2 应用

- 增加微控制器上的输入数量
- 扩展系统时钟 •

# 3 说明

录。

SN74LV393B-EP 包含八个触发器和额外的门控,可在 单个封装中实现两个独立的 4 位计数器,而且旨在于 2V 至 5.5V V<sub>CC</sub> 下运行。

该器件完全符合使用 Ioff 的部分断电应用的规范要求。 loff 电路禁用输出,从而可防止其断电时破坏性电流从 该器件回流。

器件型号	封装 <sup>(1)</sup>	封装尺寸 <sup>(2)</sup>		
SN74LV393B-EP	PW ( TSSOP , 14 )	5mm × 6.4mm		

如需了解所有可用封装,请参阅数据表末尾的可订购产品附 (1)

(2) 封装尺寸(长×宽)为标称值,并包括引脚(如适用)。



逻辑图(正逻辑)



# **Table of Contents**

1	特性	. 1
2	应用	. 1
3	说明	. 1
4	Revision History	. 2
5	Pin Configuration and Functions	3
6	Specifications	.4
	6.1 Absolute Maximum Ratings	.4
	6.2 ESD Ratings	. 4
	6.3 Recommended Operating Conditions	5
	6.4 Thermal Information	5
	6.5 Electrical Characteristics	6
	6.6 Timing Requirements, V <sub>CC</sub> = 2.5 V ± 0.2 V	6
	6.7 Timing Requirements, V <sub>CC</sub> = 3.3 V ± 0.3 V	6
	6.8 Timing Requirements, $V_{CC} = 5 V \pm 0.5 V$	6
	6.9 Switching Characteristics, V <sub>CC</sub> = 2.5 V ± 0.2 V	7
	6.10 Switching Characteristics, V <sub>CC</sub> = 3.3 V ± 0.3 V	7
	6.11 Switching Characteristics, V <sub>CC</sub> = 5 V ± 0.5 V	7
	6.12 Noise Characteristics	7
	6.13 Operating Characteristics	. 8
	6.14 Typical Characteristics	. 8

7 Parameter Measurement Information	. 9
8 Detailed Description	10
8.1 Overview	10
8.2 Functional Block Diagram	10
8.3 Feature Description.	10
8.4 Device Functional Modes	11
9 Application and Implementation	12
9.1 Application Information	12
9.2 Typical Application	12
9.3 Power Supply Recommendations	15
9.4 Layout.	15
10 Device and Documentation Support	16
10.1 Documentation Support	16
10.2 Receiving Notification of Documentation Updates	16
10.3 支持资源	16
10.4 Trademarks	16
10.5 静由放由擎告	16
10.6 术语表	16
11 Mochanical Packaging and Ordorable	10
Information	16

# **4 Revision History**

DATE	REVISION	NOTES		
August 2023	*	Initial Release		



# **5** Pin Configuration and Functions



### 图 5-1. SN74LV393B-EP: PW Package, 14-Pin TSSOP (Top View)

PIN			DESCRIPTION			
NAME	NO.		DESCRIPTION			
1CLK	1	I	Counter 1 Clock Input			
1CLR	2	I	Counter 1 Clear Input			
1Q <sub>A</sub>	3	0	Counter 1 A Output			
1Q <sub>B</sub>	4	0	Counter 1 B Output			
1Q <sub>C</sub>	5	0	Counter 1 B Output			
1Q <sub>D</sub>	6	0	ounter 1 B Output			
GND	7	G	round			
2Q <sub>D</sub>	8	0	Counter 2 D Output			
2Q <sub>C</sub>	9	0	Counter 2 C Output			
2Q <sub>B</sub>	10	0	Counter 2 B Output			
2Q <sub>A</sub>	11	0	Counter 2 A Output			
2CLR	12	I	nter 2 Clear Input			
2CLK	13	I	Counter 2 Clock Input			
V <sub>CC</sub>	14	Р	Positive supply			

#### 表 5-1. Pin Functions

(1) I = Input, O = Output, I/O = Input or Output, G = Ground, P = Power.



# 6 Specifications 6.1 Absolute Maximum Ratings

Over operating free-air temperature range (unless otherwise noted)<sup>(1)</sup>

			MIN	MAX	UNIT
V <sub>CC</sub>	Supply voltage			7	V
VI	Input voltage <sup>(2)</sup>			7	V
Vo	V <sub>O</sub> Voltage range applied to any output in the high-impedance or power-off state <sup>(2)</sup>			7	V
Vo	Output voltage <sup>(2) (3)</sup>			V <sub>CC</sub> + 0.5	V
I <sub>IK</sub>	Input clamp current	V <sub>1</sub> < 0		- 20	mA
I <sub>OK</sub>	Output clamp current	V <sub>O</sub> < 0		- 50	mA
Io	Continuous output current	$V_{O} = 0$ to $V_{CC}$		±25	mA
	Continuous current through V <sub>CC</sub> or GND			±50	mA
T <sub>stg</sub>	Storage temperature		- 65	150	°C

(1) Operation outside the Absolute Maximum Ratings may cause permanent device damage. Absolute Maximum Ratings do not imply functional operation of the device at these or any other conditions beyond those listed under Recommended Operating Conditions. If used outside the Recommended Operating Conditions but within the Absolute Maximum Ratings, the device may not be fully functional, and this may affect device reliability, functionality, performance, and shorten the device lifetime.

(2) The input and output negative-voltage ratings may be exceeded if the input and output current ratings are observed.

(3) This value is limited to 5.5 V maximum.

## 6.2 ESD Ratings

			VALUE	UNIT
	Electrostatic	Human-body model (HBM), per ANSI/ESDA/JEDEC JS-001 <sup>(1)</sup>	±2000	V
V(ESD)	discharge	Charged-device model (CDM), per ANSI/ESDA/JEDEC JS-002 <sup>(2)</sup>	±1000	v

(1) JEDEC document JEP155 states that 500-V HBM allows safe manufacturing with a standard ESD control process.

(2) JEDEC document JEP157 states that 250-V CDM allows safe manufacturing with a standard ESD control process



# 6.3 Recommended Operating Conditions

over ope	rating free-a	ir temperatur	e range (i	inless other	wise noted) $(1)$
over oper	raung nee-e	in temperatur	c range (c		wise noteu).

			MIN	MAX	UNIT	
V <sub>CC</sub>	Supply voltage		2	5.5	V	
V	High lovel input veltage	V <sub>CC</sub> = 2 V	1.5		V	
VIH	High-level input voltage	V <sub>CC</sub> = 2.3 V to 5.5 V	V <sub>CC</sub> × 0.7		v	
N/		V <sub>CC</sub> = 2 V		0.5	V	
VIL		V <sub>CC</sub> = 2.3 V to 5.5 V		V <sub>CC</sub> × 0.3	v	
VI	Input voltage		0	5.5	V	
Vo	Output voltage		0	V <sub>CC</sub>	V	
		V <sub>CC</sub> = 2 V		- 50	μA	
	High-level output current	V <sub>CC</sub> = 2.3 V to 2.7 V		- 2	mA	
юн		V <sub>CC</sub> = 3 V to 3.6 V		- 6		
		V <sub>CC</sub> = 4.5 V to 5.5 V		- 12		
		V <sub>CC</sub> = 2 V		50	μA	
		V <sub>CC</sub> = 2.3 V to 2.7 V		2	mA	
OL		V <sub>CC</sub> = 3 V to 3.6 V		6		
		V <sub>CC</sub> = 4.5 V to 5.5 V		12		
		V <sub>CC</sub> = 2.3 V to 2.7 V		200		
$\Delta t / \Delta v$	Input transition rise or fall rate	V <sub>CC</sub> = 3 V to 3.6 V		100	ns/V	
		V <sub>CC</sub> = 4.5 V to 5.5 V		20		
T <sub>A</sub>	Operating free-air temperature		- 55	125	°C	

 All unused inputs of the device must be held at V<sub>CC</sub> or GND for proper device operation. See *Implications of Slow or Floating CMOS* Inputs.

### 6.4 Thermal Information

		SN74LV393B-EP		
	THERMAL METRIC <sup>(1)</sup>	PW (TSSOP)	UNIT	
		16 PINS		
R <sub>0JA</sub>	Junction-to-ambient thermal resistance	151	°C/W	
R <sub>θ</sub> JC(top)	Junction-to-case (top) thermal resistance	80	°C/W	
R <sub>0JB</sub>	Junction-to-board thermal resistance	94.2	°C/W	
ΨJT	Junction-to-top characterization parameter	28	°C/W	
ψ́ЈВ	Junction-to-board characterization parameter	93.6	°C/W	
R <sub>0</sub> JC(bot)	Junction-to-case (bottom) thermal resistance	_	°C/W	

(1) For more information about traditional and new thermal metrics, see Semiconductor and IC Package Thermal Metrics.



## **6.5 Electrical Characteristics**

	PARAMETER	V <sub>cc</sub>	MIN	TYP MAX	UNIT
	I <sub>OH</sub> = - 50 mA	2 V to 5.5 V	V <sub>CC</sub> - 0.1		
	$I_{OH} = -2 \text{ mA}$	2.3 V	2		
VОН	I <sub>OH</sub> = -6 mA	3 V	2.48		v
	I <sub>OH</sub> = - 12 mA	4.5 V	3.8		
	I <sub>OL</sub> = 50 mA	2 V to 5.5 V		0.1	
	I <sub>OL</sub> = 2 mA	2.3 V		0.4	V
VOL	I <sub>OL</sub> = 6 mA	3 V		0.44	
	I <sub>OL</sub> = 12 mA	4.5 V		0.55	
I <sub>I</sub>	V <sub>I</sub> = 5.5 V or GND	0 V to 5.5 V		±1	μA
I <sub>CC</sub>	$V_{I} = V_{CC}$ or GND, $I_{O} = 0$	5.5 V		20	μA
I <sub>off</sub>	$V_{\rm I}$ or $V_{\rm O}$ = 0 to 5.5 V	0 V		5	μΑ
Ci	V <sub>I</sub> = V <sub>CC</sub> or GND	3.3 V		1.8	pF

over operating free-air temperature range (unless otherwise noted).

## 6.6 Timing Requirements, $V_{CC}$ = 2.5 V ± 0.2 V

timing requirements over recommended operating free-air temperature range, V<sub>CC</sub> = 2.5 V ± 0.2 V (unless otherwise noted)

			T <sub>A</sub> = 25°C -55°C to 125°C		25°C	UNIT	
			MIN	MAX	MIN	MAX	onn
t <sub>w</sub> Pulse duration	Pulse duration	CLK high or low	5		5		20
		CLR high	5		5		115
t <sub>su</sub>	Setup time	CLR inactive before CLK $\downarrow$	6		6		ns

# 6.7 Timing Requirements, $V_{CC}$ = 3.3 V ± 0.3 V

timing requirements over recommended operating free-air temperature range, V<sub>CC</sub> = 3.3 V ± 0.3 V (unless otherwise noted)

			T <sub>A</sub> = 25	°C	-55°C to 1		
			MIN	MAX	MIN	MAX	UNIT
t <sub>w</sub> Pu	Pulse duration	CLK high or low	5		5		ne
	Fuise duration	CLR high	5		5		115
t <sub>su</sub>	Setup time	CLR inactive before CLK ↓	5		5		ns

# 6.8 Timing Requirements, $V_{CC}$ = 5 V ± 0.5 V

timing requirements over recommended operating free-air temperature range, V<sub>CC</sub> = 5 V ± 0.5 V (unless otherwise noted)

			T <sub>A</sub> = 2	5°C	-55°C to	125°C	
			MIN	MAX	MIN	MAX	UNIT
t <sub>w</sub> F	Pulso duration	CLK high or low	5		5		nc
	Fuise duration	CLR high	5		5		115
t <sub>su</sub>	Setup time	CLR inactive before CLK ↓	4		4		ns



# 6.9 Switching Characteristics, V<sub>CC</sub> = 2.5 V $\pm$ 0.2 V

PARAMETER	FROM		TEST CONDITIONS	TA	TA = 25°C		-55°C to 125°C		UNIT
	(INPUT)		TEST CONDITIONS	MIN	TYP	MAX	MIN	MAX	UNIT
f <sub>max</sub>			C <sub>L</sub> = 50 pF	30	70		25		MHz
		Q <sub>A</sub>	C <sub>L</sub> = 50 pF		9.3	21.3	1	24.5	
+ .		Q <sub>B</sub>			10.9	23.9	1	27.5	
'pd	OLK	Q <sub>C</sub>			12.3	26.1	1	30	ns
		Q <sub>D</sub>			13.4	27.8	1	32	
t <sub>PHL</sub>	CLR	Q <sub>n</sub>			9.1	17.4	1	20	

over operating free-air temperature range,  $V_{CC}$  = 2.5 V ± 0.2 V (unless otherwise noted)

## 6.10 Switching Characteristics, $V_{CC}$ = 3.3 V ± 0.3 V

over operating free-air temperature range,  $V_{CC}$  = 3.3 V ± 0.3 V (unless otherwise noted)

	FROM			TA	A = 25°C		-55°C to 1	125°C	
FANAMETER	(INPUT)	10 (001701)	TEST CONDITIONS	MIN	TYP	MAX	MIN	MAX	UNIT
f <sub>max</sub>			C <sub>L</sub> = 50 pF	45	105		35		MHz
	$ \begin{array}{c}                                     $			6.7	16.7	1	19		
+ .		Q <sub>B</sub>	C <sub>L</sub> = 50 pF		7.8	19.3	1	22	
<sup>1</sup> pd		Q <sub>C</sub>			8.7	21.5	1	24.5	ns
		Q <sub>D</sub>			9.5	23.2	1	26.5	
t <sub>PHL</sub>	CLR	Q <sub>n</sub>			6.8	15.8	1	18	

# 6.11 Switching Characteristics, V<sub>CC</sub> = 5 V ± 0.5 V

over operating free-air temperature range,  $V_{CC}$  = 5 V ± 0.5 V (unless otherwise noted)

PARAMETER	FROM		TEST CONDITIONS	TA = 25°C			-55°C to 1		
	(INPUT)		TEST CONDITIONS	MIN	TYP	MAX	MIN	MAX	UNIT
f <sub>max</sub>			C <sub>L</sub> = 50 pF	85	150		75		MHz
		Q <sub>A</sub>	C <sub>L</sub> = 50 pF		4.9	10.5	1	12	
+ .		Q <sub>B</sub>			5.6	11.8	1	13.5	
<sup>1</sup> pd	OLK	Q <sub>C</sub>			6.2	13.2	1	15	ns
		Q <sub>D</sub>			6.6	14.5	1	16.5	
t <sub>PHL</sub>	CLR	Q <sub>n</sub>			5.2	10.1	1	11.5	

## 6.12 Noise Characteristics

 $V_{CC}$  = 3.3 V,  $C_{L}$  = 50 pF,  $T_{A}$  = 25°C

		SI	LINIT		
		MIN	TYP	MAX	UNIT
V <sub>OL(P)</sub>	Quiet output, maximum dynamic V <sub>OL</sub>		0.3	0.8	V
V <sub>OL(V)</sub>	Quiet output, minimum dynamic V <sub>OL</sub>		- 0.2	- 0.8	V
V <sub>OH(V)</sub>	Quiet output, minimum dynamic V <sub>OH</sub>		2.8		V
V <sub>IH(D)</sub>	High-level dynamic input voltage	2.31			V
V <sub>IL(D)</sub>	Low-level dynamic input voltage			0.99	V

(1) Characteristics for surface-mount packages only.



## 6.13 Operating Characteristics

T<sub>A</sub> = 25°C

	PARAMETER	TEST CO	ONDITIONS	Vcc	TYP	UNIT
C <sub>pd</sub>	Power dissination canacitance	$C_{1} = 50 \text{ pE}$	f – 10 MHz	3.3 V	36.1	pF
		0L - 30 pr		5 V	37.5	

## 6.14 Typical Characteristics





## **7 Parameter Measurement Information**



- A. C<sub>L</sub> includes probe and jig capacitance.
- B. Waveform 1 is for an output with internal conditions such that the output is low, except when disabled by the output control. Waveform 2 is for an output with internal conditions such that the output is high, except when disabled by the output control.
- C. All input pulses are supplied by generators having the following characteristics: PRR  $\leqslant$  1 MHz, Z\_O = 50  $\,$   $_{\Omega}$  , t\_r  $\leqslant$  3 ns,
  - and t<sub>f</sub>  $\leqslant$  3 ns.
- D. The outputs are measured one at a time, with one input transition per measurement.
- E.  $t_{PLZ}$  and  $t_{PHZ}$  are the same as  $t_{dis}$ .
- F.  $t_{PZL}$  and  $t_{PZH}$  are the same as  $t_{en}$ .
- G.  $t_{PHL}$  and  $t_{PLH}$  are the same as  $t_{pd}$ .
- H. All parameters and waveforms are not applicable to all devices.

### 图 7-1. Load Circuit and Voltage Waveforms



# 8 Detailed Description

## 8.1 Overview

The SN74LV393B-EP contains two independent 4-bit binary counters, each having a clear (CLR) and a clock ( $\overline{\text{CLK}}$ ) input. These devices change state on the negative-going transition of the  $\overline{\text{CLK}}$  pulse. N-bit binary counters can be implemented with each package, providing the capability of divide by 256. The SN74LV393B-EP has parallel outputs from each counter stage so that any sub multiple of the input count frequency is available for system timing signals.

This device is fully specified for partial-power-down applications using I<sub>off</sub>. The I<sub>off</sub> circuitry disables the outputs, preventing damaging current backflow through the device when powered down.

### 8.2 Functional Block Diagram



## 8.3 Feature Description

### 8.3.1 Balanced CMOS Push-Pull Outputs

This device includes balanced CMOS push-pull outputs. The term *balanced* indicates that the device can sink and source similar currents. The drive capability of this device may create fast edges into light loads, so routing and load conditions should be considered to prevent ringing. Additionally, the outputs of this device are capable of driving larger currents than the device can sustain without being damaged. It is important for the output power of the device to be limited to avoid damage due to overcurrent. The electrical and thermal limits defined in the *Absolute Maximum Ratings* must be followed at all times.

Unused push-pull CMOS outputs should be left disconnected.

### 8.3.2 Latching Logic

This device includes latching logic circuitry. Latching circuits commonly include D-type latches and D-type flipflops, but include all logic circuits that act as volatile memory.

When the device is powered on, the state of each latch is unknown. There is no default state for each latch at start-up.

The output state of each latching logic circuit only remains stable as long as power is applied to the device within the supply voltage range specified in the *Recommended Operating Conditions* table.



#### 8.3.3 Partial Power Down (I<sub>off</sub>)

This device includes circuitry to disable all outputs when the supply pin is held at 0 V. When disabled, the outputs will neither source nor sink current, regardless of the input voltages applied. The amount of leakage current at each output is defined by the  $I_{off}$  specification in the *Electrical Characteristics* table.

#### 8.3.4 Clamp Diode Structure

8-1 shows the inputs and outputs to this device have negative clamping diodes only.

**CAUTION** Voltages beyond the values specified in the *Absolute Maximum Ratings* table can cause damage to the device. The input and output voltage ratings may be exceeded if the input and output clampcurrent ratings are observed.



### 图 8-1. Electrical Placement of Clamping Diodes for Each Input and Output

#### 8.4 Device Functional Modes

表 8-1 lists the functional modes of the SN74LV393B-EP.

in the special grade fuble									
INPL									
CLK	CLR								
t t	L	No change							
Ļ	L	Advance to next stage							
Х	Н	All outputs L							

#### 表 8-1. Operating Mode Table

 (1) H = High Voltage Level, L = Low Voltage Level, X = Do Not Care, ↑ = Low to High transition



# 9 Application and Implementation

备注

Information in the following applications sections is not part of the TI component specification, and TI does not warrant its accuracy or completeness. TI's customers are responsible for determining suitability of components for their purposes, as well as validating and testing their design implementation to confirm system functionality.

## 9.1 Application Information

The SN74LV393B-EP is a dual 4-bit binary counter that can be used to create extended clock systems for controllers. Using a single CLK input and CLR signal, the device can output multiples of 2. Both counter banks can also be combined to divide the CLK signal by a factor of 256.

### 9.2 Typical Application



图 9-1. System Clock Divider



#### 9.2.1 Power Considerations

Ensure the desired supply voltage is within the range specified in the *Recommended Operating Conditions*. The supply voltage sets the device's electrical characteristics as described in the *Electrical Characteristics* section.

The positive voltage supply must be capable of sourcing current equal to the total current to be sourced by all outputs of the SN74LV393B-EP plus the maximum static supply current,  $I_{CC}$ , listed in the *Electrical Characteristics*, and any transient current required for switching. The logic device can only source as much current that is provided by the positive supply source. Be sure to not exceed the maximum total current through  $V_{CC}$  listed in the *Absolute Maximum Ratings*.

The ground must be capable of sinking current equal to the total current to be sunk by all outputs of the SN74LV393B-EP plus the maximum supply current, I<sub>CC</sub>, listed in the *Electrical Characteristics*, and any transient current required for switching. The logic device can only sink as much current that can be sunk into its ground connection. Be sure to not exceed the maximum total current through GND listed in the *Absolute Maximum Ratings*.

The SN74LV393B-EP can drive a load with a total capacitance less than or equal to 50 pF while still meeting all of the data sheet specifications. Larger capacitive loads can be applied; however, it is not recommended to exceed 50 pF.

The SN74LV393B-EP can drive a load with total resistance described by  $R_L \ge V_O / I_O$ , with the output voltage and current defined in the *Electrical Characteristics* table with  $V_{OH}$  and  $V_{OL}$ . When outputting in the HIGH state, the output voltage in the equation is defined as the difference between the measured output voltage and the supply voltage at the V<sub>CC</sub> pin.

Total power consumption can be calculated using the information provided in *CMOS Power Consumption and Cpd Calculation*.

Thermal increase can be calculated using the information provided in *Thermal Characteristics of Standard Linear and Logic (SLL) Packages and Devices.* 

#### CAUTION

The maximum junction temperature,  $T_{J(max)}$  listed in the *Absolute Maximum Ratings*, is an additional limitation to prevent damage to the device. Do not violate any values listed in the *Absolute Maximum Ratings*. These limits are provided to prevent damage to the device.

#### 9.2.2 Input Considerations

Input signals must cross  $V_{IL(max)}$  to be considered a logic LOW, and  $V_{IH(min)}$  to be considered a logic HIGH. Do not exceed the maximum input voltage range found in the *Absolute Maximum Ratings*.

Unused inputs must be terminated to either  $V_{CC}$  or ground. The unused inputs can be directly terminated if the input is completely unused, or they can be connected with a pull-up or pull-down resistor if the input will be used sometimes, but not always. A pull-up resistor is used for a default state of HIGH, and a pull-down resistor is used for a default state of LOW. The drive current of the controller, leakage current into the SN74LV393B-EP (as specified in the *Electrical Characteristics*), and the desired input transition rate limits the resistor size. A 10-k $\Omega$  resistor value is often used due to these factors.

The SN74LV393B-EP has CMOS inputs and thus requires fast input transitions to operate correctly, as defined in the *Recommended Operating Conditions* table. Slow input transitions can cause oscillations, additional power consumption, and reduction in device reliability.

Refer to the *Feature Description* section for additional information regarding the inputs for this device.



#### 9.2.3 Output Considerations

The positive supply voltage is used to produce the output HIGH voltage. Drawing current from the output will decrease the output voltage as specified by the  $V_{OH}$  specification in the *Electrical Characteristics*. The ground voltage is used to produce the output LOW voltage. Sinking current into the output will increase the output voltage as specified by the  $V_{OL}$  specification in the *Electrical Characteristics*.

Push-pull outputs that could be in opposite states, even for a very short time period, should never be connected directly together. This can cause excessive current and damage to the device.

Two channels within the same device with the same input signals can be connected in parallel for additional output drive strength.

Unused outputs can be left floating. Do not connect outputs directly to  $V_{CC}$  or ground.

Refer to the Feature Description section for additional information regarding the outputs for this device.

#### 9.2.4 Detailed Design Procedure

- Add a decoupling capacitor from V<sub>CC</sub> to GND. The capacitor needs to be placed physically close to the device and electrically close to both the V<sub>CC</sub> and GND pins. An example layout is shown in the *Layout* section.
- 2. Ensure the capacitive load at the output is ≤ 50 pF. This is not a hard limit; it will, however, optimize performance. This can be accomplished by providing short, appropriately sized traces from the SN74LV393B-EP to one or more of the receiving devices.
- 3. Ensure the resistive load at the output is larger than (V<sub>CC</sub> / I<sub>O(max)</sub>) Ω, which will not violate the maximum output current from the *Absolute Maximum Ratings*. Most CMOS inputs have a resistive load measured in MΩ; much larger than the minimum calculated previously.
- 4. Thermal issues are rarely a concern for logic gates; the power consumption and thermal increase, however, can be calculated using the steps provided in the application report, *CMOS Power Consumption and Cpd Calculation*.



#### 9.2.5 Application Curves





### 9.3 Power Supply Recommendations

The power supply can be any voltage between the minimum and maximum supply voltage rating located in the *Absolute Maximum Ratings* section. Each V<sub>CC</sub> terminal must have a good bypass capacitor to prevent power disturbance. For devices with a single supply, TI recommends a 0.1-  $\mu$  F capacitor; if there are multiple V<sub>CC</sub> terminals, then TI recommends a 0.01-  $\mu$  F or 0.022-  $\mu$  F capacitor for each power terminal. Multiple bypass capacitors can be paralleled to reject different frequencies of noise. Frequencies of 0.1  $\mu$  F and 1  $\mu$  F are commonly used in parallel. The bypass capacitor must be installed as close as possible to the power terminal for best results.

## 9.4 Layout

#### 9.4.1 Layout Guidelines

When using multiple bit logic devices, inputs should not float. In many cases, functions or parts of functions of digital logic devices are unused. Some examples are when only two inputs of a triple-input AND gate are used, or when only 3 of the 4-buffer gates are used. Such unused input pins must not be left unconnected because the undefined voltages at the outside connections result in undefined operational states. All unused inputs of digital logic devices must be connected to a logic high or logic low voltage, as defined by the input voltage specifications, to prevent them from floating. The logic level that must be applied to any particular unused input depends on the function of the device. Generally, the inputs are tied to GND or  $V_{CC}$ , whichever makes more sense for the logic function or is more convenient.

#### 9.4.2 Layout Example



图 9-3. Layout Example for the SN74LV393B-EP in the PW Package



# **10 Device and Documentation Support**

## **10.1 Documentation Support**

### **10.1.1 Related Documentation**

For related documentation, see the following:

- Texas Instruments, CMOS Power Consumption and Cpd Calculation
- Texas Instruments, *Power-Up Behavior of Clocked Devices*
- Texas Instruments, Introduction to Logic
- Texas Instruments, Thermal Characteristics of Standard Linear and Logic (SLL) Packages and Devices

## **10.2 Receiving Notification of Documentation Updates**

To receive notification of documentation updates—including silicon errata—go to the product folder for your device on ti.com. In the upper right-hand corner, click the *Alert me* button. This registers you to receive a weekly digest of product information that has changed (if any). For change details, check the revision history of any revised document.

## 10.3 支持资源

TI E2E<sup>™</sup> 支持论坛是工程师的重要参考资料,可直接从专家获得快速、经过验证的解答和设计帮助。搜索现有解 答或提出自己的问题可获得所需的快速设计帮助。

链接的内容由各个贡献者"按原样"提供。这些内容并不构成 TI 技术规范,并且不一定反映 TI 的观点;请参阅 TI 的《使用条款》。

## 10.4 Trademarks

TI E2E<sup>™</sup> is a trademark of Texas Instruments.

所有商标均为其各自所有者的财产。

### 10.5 静电放电警告



静电放电 (ESD) 会损坏这个集成电路。德州仪器 (TI) 建议通过适当的预防措施处理所有集成电路。如果不遵守正确的处理和安装程序,可能会损坏集成电路。

ESD 的损坏小至导致微小的性能降级,大至整个器件故障。精密的集成电路可能更容易受到损坏,这是因为非常细微的参数更改都可能会导致器件与其发布的规格不相符。

### 10.6 术语表

TI 术语表 本术语表列出并解释了术语、首字母缩略词和定义。

## 11 Mechanical, Packaging, and Orderable Information

The following pages include mechanical, packaging, and orderable information. This information is the most current data available for the designated devices. This data is subject to change without notice and revision of this document. For browser-based versions of this data sheet, refer to the left-hand navigation.



## PACKAGING INFORMATION

Orderable Device	Status (1)	Package Type	Package Drawing	Pins	Package Qty	Eco Plan (2)	Lead finish/ Ball material (6)	MSL Peak Temp (3)	Op Temp (°C)	Device Marking (4/5)	Samples
SN74LV393BMPWREP	ACTIVE	TSSOP	PW	14	3000	RoHS & Green	NIPDAU	Level-1-260C-UNLIM	-55 to 125	LV393EP	Samples
V62/23624-01XE	ACTIVE	TSSOP	PW	14	3000	TBD	Call TI	Call TI			Samples

<sup>(1)</sup> The marketing status values are defined as follows:

ACTIVE: Product device recommended for new designs.

**LIFEBUY:** TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

**PREVIEW**: Device has been announced but is not in production. Samples may or may not be available.

**OBSOLETE:** TI has discontinued the production of the device.

<sup>(2)</sup> RoHS: TI defines "RoHS" to mean semiconductor products that are compliant with the current EU RoHS requirements for all 10 RoHS substances, including the requirement that RoHS substance do not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, "RoHS" products are suitable for use in specified lead-free processes. TI may reference these types of products as "Pb-Free".

**RoHS Exempt:** TI defines "RoHS Exempt" to mean products that contain lead but are compliant with EU RoHS pursuant to a specific EU RoHS exemption.

Green: TI defines "Green" to mean the content of Chlorine (CI) and Bromine (Br) based flame retardants meet JS709B low halogen requirements of <=1000ppm threshold. Antimony trioxide based flame retardants must also meet the <=1000ppm threshold requirement.

<sup>(3)</sup> MSL, Peak Temp. - The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

<sup>(4)</sup> There may be additional marking, which relates to the logo, the lot trace code information, or the environmental category on the device.

<sup>(5)</sup> Multiple Device Markings will be inside parentheses. Only one Device Marking contained in parentheses and separated by a "~" will appear on a device. If a line is indented then it is a continuation of the previous line and the two combined represent the entire Device Marking for that device.

<sup>(6)</sup> Lead finish/Ball material - Orderable Devices may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

**Important Information and Disclaimer:**The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.



www.ti.com

# PACKAGE OPTION ADDENDUM

17-Apr-2024

PW (R-PDSO-G14)

PLASTIC SMALL OUTLINE



A. An integration of the information o

Body length does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0,15 each side.

Body width does not include interlead flash. Interlead flash shall not exceed 0,25 each side.

E. Falls within JEDEC MO-153



#### 重要声明和免责声明

TI"按原样"提供技术和可靠性数据(包括数据表)、设计资源(包括参考设计)、应用或其他设计建议、网络工具、安全信息和其他资源, 不保证没有瑕疵且不做出任何明示或暗示的担保,包括但不限于对适销性、某特定用途方面的适用性或不侵犯任何第三方知识产权的暗示担 保。

这些资源可供使用 TI 产品进行设计的熟练开发人员使用。您将自行承担以下全部责任:(1) 针对您的应用选择合适的 TI 产品,(2) 设计、验 证并测试您的应用,(3) 确保您的应用满足相应标准以及任何其他功能安全、信息安全、监管或其他要求。

这些资源如有变更,恕不另行通知。TI 授权您仅可将这些资源用于研发本资源所述的 TI 产品的应用。严禁对这些资源进行其他复制或展示。 您无权使用任何其他 TI 知识产权或任何第三方知识产权。您应全额赔偿因在这些资源的使用中对 TI 及其代表造成的任何索赔、损害、成 本、损失和债务,TI 对此概不负责。

TI 提供的产品受 TI 的销售条款或 ti.com 上其他适用条款/TI 产品随附的其他适用条款的约束。TI 提供这些资源并不会扩展或以其他方式更改 TI 针对 TI 产品发布的适用的担保或担保免责声明。

TI 反对并拒绝您可能提出的任何其他或不同的条款。

邮寄地址:Texas Instruments, Post Office Box 655303, Dallas, Texas 75265 Copyright © 2024,德州仪器 (TI) 公司