

TIDA-01477 REV B Bill of Materials

Item #	Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
1	IPCB1	1		TIDA-01477	Any	Printed Circuit Board	
2	BT1	1		BHX1-2032-PC	Memory Protection Devices	Battery Holder for CR2032, TH	Battery Holder, TH
3	C2, C3, C5, C13, C14, C17	6	0.1uF	GRM155R70J104KA01D	MuRata	CAP, CERM, 0.1 uF, 6.3 V, +/- 10%, X7R, 0402	0402
4	C4, C12	2	22uF	GRM188R60J226MEA0D	MuRata	CAP, CERM, 22 uF, 6.3 V, +/- 20%, X5R, 0603	0603
5	C8	1	100uF	C3216X5R1A107M160AC	TDK	CAP, CERM, 100 uF, 10 V, +/- 20%, X5R, 1206_190	1206_190
6	C16	1	0.1uF	GRM155R71C104KA88D	MuRata	CAP, CERM, 0.1 uF, 16 V, +/- 10%, X7R, 0402	0402
7	C19, C34	2	3.6pF	GRM1555C1H3R6CA01D	MuRata	CAP, CERM, 3.6 pF, 50 V, +/- 5%, C0G/NP0, 0402	0402
8	C20, C35	2	100pF	GRM1555C1H101JA01D	MuRata	CAP, CERM, 100 pF, 50 V, +/- 5%, C0G/NP0, 0402	0402
9	C21	1	2.7pF	GRM1555C1H2R7CA01D	MuRata	CAP, CERM, 2.7 pF, 50 V, +/- 5%, C0G/NP0, 0402	0402
10	C22	1	6.2pF	GRM1555C1H6R2CA01D	MuRata	CAP, CERM, 6.2 pF, 50 V, +/- 5%, C0G/NP0, 0402	0402
11	C23	1	1uF	GRM188R70J105KA01D	MuRata	CAP, CERM, 1 uF, 6.3 V, +/- 10%, X7R, 0603	0603
12	C24	1	3pF	GRM1555C1H3R6CA01D	MuRata	CAP, CERM, 3 pF, 50 V, +/- 5%, C0G/NP0, 0402	0402
13	C26, C27	2	2200pF	C1005X7R1H222K	TDK	CAP, CERM, 2200 pF, 50 V, +/- 10%, X7R, 0402	0402
14	C29, C30	2	12pF	06035A120JAT2A	AVX	CAP, CERM, 12 pF, 50 V, +/- 5%, C0G/NP0, 0603	0603
15	C31	1	0.1uF	GRM155R71A104KA01D	MuRata	CAP, CERM, 0.1 uF, 10 V, +/- 10%, X7R, 0402	0402
16	C32	1	10uF	GRM21BR71A106KE51L	MuRata	CAP, CERM, 10 uF, 10 V, +/- 10%, X7R, 0805	0805
17	C33	1	22uF	CL21B226MQQNNNE	Samsung	CAP, CERM, 22 uF, 6.3 V, +/- 20%, X7R, 0805_140	0805_140
18	D1	1	5V	1SS315TPH3F	Toshiba	Diode, Schottky, 5 V, 0.03 A, SOD-323	SOD-323
19	E1	1		ANTENNA_HELICAL	N/A	PCB Antenna. There is nothing to buy or mount.	Antenna
20	H1, H2, H3, H4	4		NY PMS 440 0025 PH	B&F Fastener Supply	Machine Screw, Round, #4-40 x 1/4, Nylon, Phillips panhead	Screw
21	H5, H6, H7, H8	4		1902C	Keystone	Standoff, Hex, 0.5"L #4-40 Nylon	Standoff
22	J1	1		87898-0204	Molex	Header, 2.54 mm, 2x1, Gold, R/A, SMT	Header, 2.54 mm, 2x1, R/A, SMT
23	J2	1		61300211121	Würth Elektronik eiSos	Header, 2.54 mm, 2x1, Gold, TH	Header, 2.54mm, 2x1, TH
24	J5	1		GRPB052VWVN-RC	Sullins Connector Solutions	Header, 50mil, 5x2, Gold, TH	Header, 5x2, 50mil
25	J6	1		61300311121	Würth Elektronik	Header, 2.54 mm, 3x1, Gold, TH	Header, 2.54mm, 3x1, TH
26	L1	1	1500 ohm	BLM18HE152SN1D	MuRata	Ferrite Bead, 1500 ohm @ 100 MHz, 0.5 A, 0603_950	0603_950
27	L2	1	6.8uH	MLZ2012N6R8LT000	TDK	Inductor, Multilayer, Ferrite, 6.8 uH, 0.11 A, 0.25 ohm, SMD	0805
28	L3	1	6.8nH	LQG15HS6N8J02D	MuRata	Inductor, Multilayer, Air Core, 6.8 nH, 0.3 A, 0.24 ohm, SMD	0402 polarized
29	L4, L9	2	7.5nH	LQG15HS7N5J02D	MuRata	Inductor, Multilayer, Air Core, 7.5 nH, 0.3 A, 0.24 ohm, SMD	0402 polarized
30	L5, L6	2	6.8nH	LQW15AN6N8G00D	MuRata	Inductor, Wirewound, 6.8 nH, 0.7 A, 0.09 ohm, SMD	1x.5x.5mm
31	L7	1	3.3uH	VLF302515MT-3R3M	TDK	Inductor, Shielded, Ferrite, 3.3 uH, 1.23 A, 0.06 ohm, SMD	IND_3x1.5x3mm
32	L8	1	27nH	LQG15HS27NJO2D	MuRata	Inductor, Multilayer, Air Core, 27 nH, 0.3 A, 0.46 ohm, SMD	0402 polarized
33	L10	1	8.2nH	LQG15HS8N2J02D	MuRata	Inductor, Multilayer, Air Core, 8.2 nH, 0.3 A, 0.24 ohm, SMD	0402 polarized
34	R1, R3, R4, R8, R12, R17, R18, R19	8	0	CRCW04020000Z0ED	Vishay-Dale	RES, 0, 5%, 0.063 W, 0402	0402
35	R2	1	0	CRCW08050000Z0EA	Vishay-Dale	RES, 0, 5%, 0.125 W, 0805	0805
36	R5	1	40.2k	CRCW040240K2FKED	Vishay-Dale	RES, 40.2 k, 1%, 0.063 W, 0402	0402
37	R6	1	48.7k	CRCW040248K7FKED	Vishay-Dale	RES, 48.7 k, 1%, 0.063 W, 0402	0402
38	R7, R9, R10, R11, R21	5	10.0k	CRCW040210K0FKED	Vishay-Dale	RES, 10.0 k, 1%, 0.063 W, 0402	0402
39	R15, R16	2	47.5k	CRCW040247K5FKED	Vishay-Dale	RES, 47.5 k, 1%, 0.063 W, 0402	0402
40	S1, S2	2		B3U-1000P	Omron Electronic Components	SWITCH TACTILE SPST-NO 0.05A 12V	3x1.6x2.5mm
41	S3	1		A6S-4104-H	Omron Electronic Components	DIP Switch, 4 position slide actuator, SPST, SMD	SMT DIP switch
42	SH-J1, SH-J2	2	1x2	2SN-BK-G	Samtec	Shunt, 2mm, Gold plated, Black	2mm Shunt, Closed Top
43	TP1, TP2, TP3, TP4, TP5, TP6, TP7, TP8	8	SMT	5015	Keystone	Test Point, Miniature, SMT	Testpoint_Keystone_Miniature
44	U1	1		TPS22860DBVR	Texas Instruments	Ultra-Low Leakage Load Switch, DBV0006A	DBV0006A
45	U2	1		TPL5111DDCR	Texas Instruments	Nano-power System Timer for Power Gating, DDC0006A	DDC0006A
46	U3	1		HDC2010YPAR	Texas Instruments	HDC2010 Low Power Humidity and Temperature Digital Sensor, YPA0006ABAB (DSBGA-6)	YPA0006ABAB
47	U5, U6, U7, U8	4		TPD1E10B06DPYR	Texas Instruments	ESD in 0402 Package with 10 pF Capacitance and 6 V Breakdown, 1 Channel, -40 to +125 degC, 2-pin X2SON (DPY), Green (RoHS & no Sb/Bi)	DPY0002A
48	U9	1		TPS61291DRV	Texas Instruments	LOW Iq BOOST CONVERTER WITH BYPASS OPERATION, DRV0006A	DRV0006A
49	U10	1		CC1310F128RGZR	Texas Instruments	Sub-1 GHz and 2.4 GHz Multi-standard RF IC Family, RGZ0048A	RGZ0048A
50	Y1	1		TSX-3225 24.0000MF20G-AC3	Epson	Crystal, 24 MHz, 9 pF, SMD	SMD, 4-Leads, Body 2.65x3.35mm, Height 0.6mm
51	Y2	1		FC-12M 32.7680KA-A3	Epson	Crystal, 32.768kHz, 12.5pF, SMD	Crystal 2.05x.6x1.2mm
52	C1, C6, C7, C15, C25, C28	0		Used in BOM report	Used in BOM report	CAP, CERM, xxxF, xxV, [TempCo], xx%, [PackageReference]	Used in PnP output and some BOM reports
53	FID1, FID2, FID3, FID4, FID5, FID6	0		N/A	N/A	Fiducial mark. There is nothing to buy or mount.	N/A
54	J3	0		CONSMA001-SMD-G	Linx Technologies	Jack, SMA, PCB, Gold, SMT	SMA Jack
55	J4	0		TSW-106-07-G-S	Samtec	Header, 100mil, 6x1, Gold, TH	6x1 Header
56	R13, R14	0		Used in BOM report	Used in BOM report	RES, xxx ohm, x%, xW, [PackageReference]	Used in PnP output and some BOM reports
57	R20	0	0	CRCW04020000Z0ED	Vishay-Dale	RES, 0, 5%, 0.063 W, 0402	0402
58	R22, R23	0	10.0k	CRCW040210K0FKED	Vishay-Dale	RES, 10.0 k, 1%, 0.063 W, 0402	0402

IMPORTANT NOTICE AND DISCLAIMER

TI PROVIDES TECHNICAL AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS AND IMPLIED, INCLUDING WITHOUT LIMITATION ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for skilled developers designing with TI products. You are solely responsible for (1) selecting the appropriate TI products for your application, (2) designing, validating and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, or other requirements. These resources are subject to change without notice. TI grants you permission to use these resources only for development of an application that uses the TI products described in the resource. Other reproduction and display of these resources is prohibited. No license is granted to any other TI intellectual property right or to any third party intellectual property right. TI disclaims responsibility for, and you will fully indemnify TI and its representatives against, any claims, damages, costs, losses, and liabilities arising out of your use of these resources.

TI's products are provided subject to TI's Terms of Sale (www.ti.com/legal/termsofsale.html) or other applicable terms available either on ti.com or provided in conjunction with such TI products. TI's provision of these resources does not expand or otherwise alter TI's applicable warranties or warranty disclaimers for TI products.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2018, Texas Instruments Incorporated