

Filename: ProA6D.tmp  
 Variant: 001  
 Generated: 5/9/2016 3:59:49 PM  
 TID #: PMP15003



PMP15003 REV E1 Bill of Materials

Item #	Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
1	!PCB1	1		PMP15003	Any	Printed Circuit Board	
2	C3, C11	2	0.1uF	C3216X7R2A104K	TDK	CAP, CERM, 0.1 µF, 100 V, +/- 10%, X7R, 1206	1206
3	C4, C25, C26, C28	4	0.1uF	C1608X7R1E104K	TDK	CAP, CERM, 0.1 µF, 25 V, +/- 10%, X7R, 0603	0603
4	C5, C6	2	0.1uF	C2012X7R2A104K	TDK	CAP, CERM, 0.1 µF, 100 V, +/- 10%, X7R, 0805	0805
5	C7, C8, C9, C10, C12, C13, C14, C15	8	4.7uF	C3225X7S2A475K200AE	TDK	CAP, CERM, 4.7 µF, 100 V, +/- 10%, X7S, 1210	1210
6	C16	1	0.1uF	C2012X7R2A104K125AA	TDK	CAP, CERM, 0.1 µF, 100 V, +/- 10%, X7R, 0805	0805
7	C17	1	100pF	C1608C0G1H101J	TDK	CAP, CERM, 100 pF, 50 V, +/- 5%, C0G/NP0, 0603	0603
8	C18, C19	2	1000pF	C1608C0G2A102J	TDK	CAP, CERM, 1000 pF, 100 V, +/- 5%, C0G/NP0, 0603	0603
9	C20	1	0.1uF	C1608X7R1H104K	TDK	CAP, CERM, 0.1 µF, 50 V, +/- 10%, X7R, 0603	0603
10	C23	1	10pF	C1608C0G1H100D	TDK	CAP, CERM, 10 pF, 50 V, +/- 5%, C0G/NP0, 0603	0603
11	C24	1	2.2uF	C2012X7R1C225K	TDK	CAP, CERM, 2.2 µF, 16 V, +/- 10%, X7R, 0805	0805
12	C27	1	3300pF	GRM188R71E332KA01D	MuRata	CAP, CERM, 3300 pF, 25 V, +/- 10%, X7R, 0603	0603
13	C29	1	0.033uF	GRM216R71E333KA01D	MuRata	CAP, CERM, 0.033 µF, 25 V, +/- 10%, X7R, 0805	0805
14	D1	1	100V	PDS3100Q-13	Diodes Inc.	Diode, Schottky, 100 V, 3 A, AEC-Q101, PowerDI5	PowerDI5
15	GND	1	Black	5001	Keystone	Test Point, Miniature, Black, TH	Black Miniature Testpoint
16	J2	1		1727023	Phoenix Contact	Terminal Block Receptacle, 3x1, 3.81mm, R/A, TH	Term Block, 3 pos
17	J3	1		1727010	Phoenix Contact	Conn Term Block, 2POS, 3.81mm, TH	2POS Terminal Block
18	J4	1		TSW-103-07-T-S	Samtec	Header, 2.54 mm, 3x1, Tin, TH	Header, 2.54 mm, 3x1, TH
19	L1	1	3.3uH	CLF7045T-3R3N	TDK	Inductor, Shielded, Ferrite, 3.3 µH, 5 A, 0.0213 ohm, SMD	Inductor, 6.2x4.5x5.9mm
20	L2	1	22uH	IHLPL4040DZER220M8A	Vishay-Dale	Inductor, Shielded Drum Core, Powdered Iron, 22 µH, 4.1 A, 0.0705 ohm, AEC-Q200 Grade 0, SMD	IHLPL-4040DZ
21	L3, L4	2	160 ohm	HI1206T161R-10	Laird-Signal Integrity Products	Ferrite Bead, 160 ohm @ 100 MHz, 6 A, 1206	1206
22	L5, L6	2		74408941010	Würth Electronics Inc	Inductor, Fixed, 1uH, 3A, 0.0295 ohm, SMD	1919 (4848 Metric)
23	NEG(-), POS (+)	2	Double	1502-2	Keystone	Terminal, Turret, TH, Double	Keystone1502-2
24	Q3	1	100V	STL8N10LF3	STMicroelectronics	MOSFET, N-CH, 100 V, 20 A, AEC-Q101, 8-PowerVDFN	8-PowerVDFN
25	R1	1	0.1	MCR25JZHFLR100	Rohm	RES, 0.1, 1%, 0.5 W, 1210	1210
26	R3	1	10.0	CRCW120610R0FKFA	Vishay-Dale	RES, 10.0, 1%, 0.25 W, 1206	1206
27	R4	1	487k	CRCW0603487KFKFA	Vishay-Dale	RES, 487 k, 1%, 0.1 W, 0603	0603
28	R6, R14, R15	3	10.0	CRCW060310R0FKFA	Vishay-Dale	RES, 10.0, 1%, 0.1 W, 0603	0603
29	R7	1	100	CRCW0603100RFKFA	Vishay-Dale	RES, 100, 1%, 0.1 W, 0603	0603
30	R8	1	1.0k	CRCW06031K00JNEA	Vishay-Dale	RES, 1.0 k, 5%, 0.1 W, 0603	0603
31	R10, R16, R17	3	100k	CRCW0603100KFKEA	Vishay-Dale	RES, 100 k, 1%, 0.1 W, 0603	0603
32	R11	1	0.04	WSL2010R0400FEA18	Vishay Dale	RES, 0.04 ohm, 1%, 1W, 2010	2010 (5025 Metric)
33	R12	1	10.0k	CRCW060310K0FKFA	Vishay-Dale	RES, 10.0 k, 1%, 0.1 W, 0603	0603
34	R13	1	102k	CRCW0603102KFKEA	Vishay-Dale	RES, 102 k, 1%, 0.1 W, 0603	0603
35	R18	1	20.0k	CRCW060320K0FKFA	Vishay-Dale	RES, 20.0 k, 1%, 0.1 W, 0603	0603
36	R19	1	1.43k	CRCW06031K43FKFA	Vishay-Dale	RES, 1.43 k, 1%, 0.1 W, 0603	0603
37	R21	1	23.2k	CRCW060323K2FKFA	Vishay-Dale	RES, 23.2 k, 1%, 0.1 W, 0603	0603
38	SH-J4	1		60900213521	Würth Elektronik	Shunt, 2.54mm, Gold, Red	Shunt, 2.54mm, Red
39	TP2, TP4, TP6, TP7	4	Orange	5003	Keystone	Test Point, Miniature, Orange, TH	Orange Miniature Testpoint
40	U1	1		TPS92691QPWPRQ1	Texas Instruments	Multi-Topology LED Driver with Rail-to-Rail Current Sense Amplifier, PWP0016J	PWP0016J
41	C21, C22	0	0.01uF	C1608X8R2A103K	TDK	CAP, CERM, 0.01 µF, 100 V, +/- 10%, X8R, 0603	0603
42	FID1, FID2, FID3	0		N/A	N/A	Fiducial mark. There is nothing to buy or mount.	Fiducial
43	R20	0	4.99Meg	CRCW06034M99FKFA	Vishay-Dale	RES, 4.99 M, 1%, 0.1 W, 0603	0603
44	TP3, TP5	0	Double	1502-2	Keystone	Terminal, Turret, TH, Double	Keystone1502-2

## IMPORTANT NOTICE FOR TI REFERENCE DESIGNS

Texas Instruments Incorporated ("TI") reference designs are solely intended to assist designers ("Designer(s)") who are developing systems that incorporate TI products. TI has not conducted any testing other than that specifically described in the published documentation for a particular reference design.

TI's provision of reference designs and any other technical, applications or design advice, quality characterization, reliability data or other information or services does not expand or otherwise alter TI's applicable published warranties or warranty disclaimers for TI products, and no additional obligations or liabilities arise from TI providing such reference designs or other items.

TI reserves the right to make corrections, enhancements, improvements and other changes to its reference designs and other items.

Designer understands and agrees that Designer remains responsible for using its independent analysis, evaluation and judgment in designing Designer's systems and products, and has full and exclusive responsibility to assure the safety of its products and compliance of its products (and of all TI products used in or for such Designer's products) with all applicable regulations, laws and other applicable requirements. Designer represents that, with respect to its applications, it has all the necessary expertise to create and implement safeguards that (1) anticipate dangerous consequences of failures, (2) monitor failures and their consequences, and (3) lessen the likelihood of failures that might cause harm and take appropriate actions. Designer agrees that prior to using or distributing any systems that include TI products, Designer will thoroughly test such systems and the functionality of such TI products as used in such systems. Designer may not use any TI products in life-critical medical equipment unless authorized officers of the parties have executed a special contract specifically governing such use. Life-critical medical equipment is medical equipment where failure of such equipment would cause serious bodily injury or death (e.g., life support, pacemakers, defibrillators, heart pumps, neurostimulators, and implantables). Such equipment includes, without limitation, all medical devices identified by the U.S. Food and Drug Administration as Class III devices and equivalent classifications outside the U.S.

Designers are authorized to use, copy and modify any individual TI reference design only in connection with the development of end products that include the TI product(s) identified in that reference design. HOWEVER, NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER TI INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT OF TI OR ANY THIRD PARTY IS GRANTED HEREIN, including but not limited to any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services, or a warranty or endorsement thereof. Use of the reference design or other items described above may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

TI REFERENCE DESIGNS AND OTHER ITEMS DESCRIBED ABOVE ARE PROVIDED "AS IS" AND WITH ALL FAULTS. TI DISCLAIMS ALL OTHER WARRANTIES OR REPRESENTATIONS, EXPRESS OR IMPLIED, REGARDING THE REFERENCE DESIGNS OR USE OF THE REFERENCE DESIGNS, INCLUDING BUT NOT LIMITED TO ACCURACY OR COMPLETENESS, TITLE, ANY EPIDEMIC FAILURE WARRANTY AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

TI SHALL NOT BE LIABLE FOR AND SHALL NOT DEFEND OR INDEMNIFY DESIGNERS AGAINST ANY CLAIM, INCLUDING BUT NOT LIMITED TO ANY INFRINGEMENT CLAIM THAT RELATES TO OR IS BASED ON ANY COMBINATION OF PRODUCTS AS DESCRIBED IN A TI REFERENCE DESIGN OR OTHERWISE. IN NO EVENT SHALL TI BE LIABLE FOR ANY ACTUAL, DIRECT, SPECIAL, COLLATERAL, INDIRECT, PUNITIVE, INCIDENTAL, CONSEQUENTIAL OR EXEMPLARY DAMAGES IN CONNECTION WITH OR ARISING OUT OF THE REFERENCE DESIGNS OR USE OF THE REFERENCE DESIGNS, AND REGARDLESS OF WHETHER TI HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

TI's standard terms of sale for semiconductor products (<http://www.ti.com/sc/docs/stdterms.htm>) apply to the sale of packaged integrated circuit products. Additional terms may apply to the use or sale of other types of TI products and services.

Designer will fully indemnify TI and its representatives against any damages, costs, losses, and/or liabilities arising out of Designer's non-compliance with the terms and provisions of this Notice.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265  
Copyright © 2016, Texas Instruments Incorporated