

PMP9291 REV rev4 Bill of Materials

Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
I PCB	1		PMP9291	Any	Printed Circuit Board	
C30	1	1000pF	VJ1210Y102KXGAT5Z	Vishay-Vitramon	Ceramic, X7R, 1000V, 10%	1210
C31, C32	2	2.2uF	GRM21BR71E225KA73L	MuRata	CAP, CERM, 2.2uF, 25V, +/-10%, X7R, 0805	0805
C33	1	0.01uF	GRM188R71C103KA01D	MuRata	CAP, CERM, 0.01uF, 16V, +/-10%, X7R, 0603	0603
C34, C41	2	0.1uF	06035C104KAT2A	AVX	CAP, CERM, 0.1uF, 50V, +/-10%, X7R, 0603	0603
C35	1	1uF	C0603C105K4PACTU	Kemet	CAP, CERM, 1uF, 16V, +/-10%, X5R, 0603	0603
C36	1	0.01uF	06031C103JAT2A	AVX	CAP, CERM, 0.01uF, 100V, +/-5%, X7R, 0603	0603
C37, C38	2	2.2uF	GRM31CR61H225KA88L	MuRata	CAP, CERM, 2.2uF, 50V, +/-10%, X5R, 1206	1206
C39	1	2.2uF	C2012X7R1C225K	TDK	CAP, CERM, 2.2uF, 16V, +/-10%, X7R, 0805	0805
D4	1	100V	BAS316,115	NXP Semiconductor	Diode, Ultrafast, 100V, 0.25A, SOD-323	SOD-323
GND1, GND2, GNDin	3	Black	5001	Keystone	Test Point, TH, Miniature, Black	Keystone5001
H1, H2, H3, H4	4		NY PMS 440 0025 PH	B&F Fastener Supply	Machine Screw, Round, #4-40 x 1/4, Nylon, Philips panhead	Screw
H5, H6, H7, H8	4		1902C	Keystone	Standoff, Hex, 0.5"L #4-40 Nylon	Standoff
Q13	1	60V	CSD18537NQ5A	Texas Instruments	MOSFET, N-CH, 60V, 50A, SON 5x6mm	SON 5x6mm
Q14	1	0.2V	MMBT3904-7-F	Diodes Inc.	Transistor, NPN, 40V, 0.2A, SOT-23	SOT-23
Q15	1	0.25V	MMBT3906	Fairchild Semiconductor	Transistor, PNP, 40V, 0.2A, SOT-23	SOT-23
R1, R32	2	0	CRCW12060000Z0EA	Vishay-Dale	RES, 0 ohm, 5%, 0.25W, 1206	1206
R3	1	0	CRCW08050000Z0EA	Vishay-Dale	RES, 0 ohm, 5%, 0.125W, 0805	0805
R27	1	10	CRCW060310R0JNEA	Vishay-Dale	RES, 10 ohm, 5%, 0.1W, 0603	0603
R29	1	30k	CRCW060310K0FKEA	Vishay-Dale	RES, 10.0k ohm, 1%, 0.1W, 0603	0603
R30	1	137k	CRCW0603137KFKEA	Vishay-Dale	RES, 137k ohm, 1%, 0.1W, 0603	0603
R31	1	127k	CRCW0805127KFKEA	Vishay-Dale	RES, 127k ohm, 1%, 0.125W, 0805	0805
R33	1	6.04k	CRCW06036K04FKEA	Vishay-Dale	RES, 6.04k ohm, 1%, 0.1W, 0603	0603
R35	1	2.00k	CRCW06032K00FKEA	Vishay-Dale	RES, 2.00k ohm, 1%, 0.1W, 0603	0603
R36	1	0	CRCW060310R0JNEA	Vishay-Dale	RES, 10 ohm, 5%, 0.1W, 0603	0603
R37	1	1.00k	CRCW06031K00FKEA	Vishay-Dale	RES, 1.00k ohm, 1%, 0.1W, 0603	0603
SW1, SW2, Vin, Vo1, Vo2	5	Red	5000	Keystone	Test Point, TH, Miniature, Red	Keystone5000
T1	1		VP2xxxx_VPH2xxxx	Cooper Bussmann Coiltronics	1:1:1:1:1 Turns Ratio Versatile Transformers	VP2_VPH2
U2	1		LM5017MRX/NOPB	Texas Instruments	100V, 600mA Constant On-Time Synchronous Buck Regulator, DDA0008B	DDA0008B
C40	0	2.2uF	GRM21BR71E225KA73L	MuRata	CAP, CERM, 2.2uF, 25V, +/-10%, X7R, 0805	0805
D6	0	45V	CD0603-B0240	Bourns	Diode, Schottky, 45V, 0.2A, 0603 Diode	0603 Diode
FID1, FID2, FID3	0		N/A	N/A	Fiducial mark. There is nothing to buy or mount.	Fiducial
R28	0		CRCW06032K00FKEA	Vishay-Dale	RES, 2.00k ohm, 1%, 0.1W, 0603	0603
R34	0	8.25k	CRCW08058K25FKEA	Vishay-Dale	RES, 8.25k ohm, 1%, 0.125W, 0805	0805

IMPORTANT NOTICE FOR TI REFERENCE DESIGNS

Texas Instruments Incorporated ("TI") reference designs are solely intended to assist designers ("Buyers") who are developing systems that incorporate TI semiconductor products (also referred to herein as "components"). Buyer understands and agrees that Buyer remains responsible for using its independent analysis, evaluation and judgment in designing Buyer's systems and products.

TI reference designs have been created using standard laboratory conditions and engineering practices. **TI has not conducted any testing other than that specifically described in the published documentation for a particular reference design.** TI may make corrections, enhancements, improvements and other changes to its reference designs.

Buyers are authorized to use TI reference designs with the TI component(s) identified in each particular reference design and to modify the reference design in the development of their end products. HOWEVER, NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER TI INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY THIRD PARTY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT, IS GRANTED HEREIN, including but not limited to any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services, or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

TI REFERENCE DESIGNS ARE PROVIDED "AS IS". TI MAKES NO WARRANTIES OR REPRESENTATIONS WITH REGARD TO THE REFERENCE DESIGNS OR USE OF THE REFERENCE DESIGNS, EXPRESS, IMPLIED OR STATUTORY, INCLUDING ACCURACY OR COMPLETENESS. TI DISCLAIMS ANY WARRANTY OF TITLE AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, QUIET ENJOYMENT, QUIET POSSESSION, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS WITH REGARD TO TI REFERENCE DESIGNS OR USE THEREOF. TI SHALL NOT BE LIABLE FOR AND SHALL NOT DEFEND OR INDEMNIFY BUYERS AGAINST ANY THIRD PARTY INFRINGEMENT CLAIM THAT RELATES TO OR IS BASED ON A COMBINATION OF COMPONENTS PROVIDED IN A TI REFERENCE DESIGN. IN NO EVENT SHALL TI BE LIABLE FOR ANY ACTUAL, SPECIAL, INCIDENTAL, CONSEQUENTIAL OR INDIRECT DAMAGES, HOWEVER CAUSED, ON ANY THEORY OF LIABILITY AND WHETHER OR NOT TI HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES, ARISING IN ANY WAY OUT OF TI REFERENCE DESIGNS OR BUYER'S USE OF TI REFERENCE DESIGNS.

TI reserves the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques for TI components are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

Reproduction of significant portions of TI information in TI data books, data sheets or reference designs is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards that anticipate dangerous failures, monitor failures and their consequences, lessen the likelihood of dangerous failures and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in Buyer's safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed an agreement specifically governing such use.

Only those TI components that TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components that have **not** been so designated is solely at Buyer's risk, and Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.