

Engineering Bill of Materials



Project Name:	UCC28630 REFERENCE DESIGN
Project File:	PMP9208.PrjPCB

										91
Item	Designator	Description	Manufacturer	PartNumber	Quantity	Supplier 1	Supplier Part Number 1	Supplier 2	Supplier Part Number 2	
1	IPC B1	Printed Circuit Board	Any	PMP9208	1					
2	BR1	Diode, Switching-Bridge, 800V, 4A, TH	Vishay-Semiconductor	GBU4K-E3/45	1	Digi-Key	GBU4K-E3/45GI-ND	Mouser	625-GBU4K-E3	
3	C1	CAP, Film, 0.33uF, 630V, +/-20%, TH	Vishay-Bcomponents	BFC233840334	1	Mouser	594-22233840334	Farnell	1166449	
4	C2	CAP, AL, 22uF, 25V, +/-20%, TH	Rubycon	25ML22MEFC5X5	1	Digi-Key	25ML22MEFC5X5-ND	Farnell	8126402	
5	C3	CAP, CERM, 1uF, 25V, +/-10%, X7R, 1206	AVX	12063C105KAT2A	1	Digi-Key	478-1567-1-ND	Mouser	581-12063C105K	
6	C4	CAP, CERM, 0.1uF, 25V, +/-10%, X7R, 0603	Kemet	C0603C104K3RACTU	1	Digi-Key	399-1281-1-ND	Mouser	80-C0603C104K3R	
7	C5	CAP, AL, 100uF, 400V, +/-20%, TH	Rubycon	400KXW100MEFC16X30	1	Digi-Key	400KXW100MEFC16X30-ND	Farnell	8126844	
8	C6	CAP, CERM, 120pF, 50V, +/-5%, C0G/NP0, 0603	AVX	06035A121JAT2A	1	Digi-Key	478-1176-1-ND	Mouser	581-06035A121J	
9	C7	CAP, AL, 27uF, 400V, +/-20%, TH	Nichicon	UCY2G270MHD1TO	1	Digi-Key	493-4825-1-ND			
10	C9	CAP, CERM, 2200pF, 250V, +/-20%, E, Disc 10x8mm	MuRata	DE1E3KX222MA5BA01	1	Digi-Key	490-7048-ND	Mouser	81-DE1010E222M	
11	C11	CAP, AL, 680uF, 35V, +/-20%, 0.019 ohm, TH	Nichicon	UHW1V681MPD6	1	Digi-Key	493-6804-ND			
12	C12	CAP, AL, 680uF, 35V, +/-20%, 0.019 ohm, TH	Nichicon	UHW1V681MPD6	1	Digi-Key	493-6804-ND			
13	C13	CAP, CERM, 1uF, 50V, +/-10%, X7R, 1206	TDK	C3216X7R1H105K	1	Digi-Key	445-1423-1-ND	Farnell	1907358	
14	C14	CAP, CERM, 1000pF, 100V, +/-10%, X7R, 0805	AVX	08051C102KAT2A	1	Digi-Key	478-1352-1-ND	Mouser	581-08051C102K	
15	C16	CAP, CERM, 10pF, 200V, +/-5%, C0G/NP0, 1206	AVX	12062A100JAT2A	1	Digi-Key	12062A100JAT2A-ND	Mouser	581-12062A100JAT2A	
16	C17	CAP, CERM, 10pF, 50V, +/-5%, C0G/NP0, 0603	AVX	06035A100JAT2A	1	Digi-Key	478-1163-1-ND	Mouser	581-06035A100J	
17	D1	Diode, Ultrafast, 200V, 1A, SMA	Diodes Inc.	ES1D-13-F	1	Digi-Key	ES1D-FDICT-ND	Mouser	621-ES1D-F	
18	D2	Diode, P-N, 1000V, 1A, TH	Fairchild Semiconductor	1N4007	1	Digi-Key	1N4007FSCT-ND	Mouser	512-1N4007	
19	D3	Diode, P-N, 1000V, 1A, TH	Fairchild Semiconductor	1N4007	1	Digi-Key	1N4007FSCT-ND	Mouser	512-1N4007	
20	D4	Diode, Switching, 70V, 0.25A, SOT-23	Vishay-Semiconductor	BAV70-V	1	Digi-Key	BAV70-V-GS08CT-ND	Mouser	625-BAV70-V	
21	D5	Diode, Ultrafast, 100V, 0.25A, SOD-323	NXP Semiconductor	BAS316,115	1	Digi-Key	568-5003-1-ND	Farnell	8734275	
22	D6	Diode, Ultrafast, 600V, 1A, SMB	Diodes Inc.	MURS160-13-F	1	Digi-Key	MURS160-FDICT-ND	Mouser	621-MURS160-F	
23	D7	Diode, Schottky, 100V, 15A, TH	ON Semiconductor	NTST30100CTG	1	Digi-Key	NTST30100CTG-ND	Mouser	863-NTST30100CTG	
24	D8	Diode, Zener, 82V, 550mW, SMB	ON Semiconductor	1SMB5947BT3G	1	Mouser	863-1SMB5947BT3G	Farnell	1887115	
25	D9	Diode, Zener, 100V, 550mW, SMB	ON Semiconductor	1SMB5949BT3G	1	Mouser	863-1SMB5949BT3G	Farnell	1431186	
26	D11	Diode, Ultrafast, 100V, 0.25A, SOD-323	NXP Semiconductor	BAS316,115	1	Digi-Key	568-5003-1-ND	Farnell	8734275	
27	D12	Diode, Zener, 5.6V, 200mW, SOD-323	Diodes Inc.	MMSZ5232BS-7-F	1	Digi-Key	MMSZ5232BS-FDICT-ND	Mouser	621-MMSZ5232BS-F	
28	F1	Fuse, 3.15A, 250V, TH	Littelfuse	39213150000	1	Digi-Key	F5504CT-ND	Mouser	576-3921315000	
29	H1	Standoff, Hex, 1"L #6-32 Nylon, M-F	Keystone	4820	1	Digi-Key	4820K-ND	Mouser	534-4820	
30	H2	Standoff, Hex, 1"L #6-32 Nylon, M-F	Keystone	4820	1	Digi-Key	4820K-ND	Mouser	534-4820	
31	H3	Standoff, Hex, 1"L #4-40 Nylon	Keystone	1902E	1	Digi-Key	1902EK-ND			
32	H4	Standoff, Hex, 1"L #4-40 Nylon	Keystone	1902E	1	Digi-Key	1902EK-ND			
33	H5	Standoff, Hex, 1"L #6-32 Nylon, M-F	Keystone	4820	1	Digi-Key	4820K-ND	Mouser	534-4820	
34	H6	Standoff, Hex, 1"L #6-32 Nylon, M-F	Keystone	4820	1	Digi-Key	4820K-ND	Mouser	534-4820	
35	H7	Standoff, Hex, 1"L #4-40 Nylon	Keystone	1902E	1	Digi-Key	1902EK-ND			
36	H8	Standoff, Hex, 1"L #4-40 Nylon	Keystone	1902E	1	Digi-Key	1902EK-ND			
37	H9	1350F Tape	3M	1350F-1 25MM	1					
38	H10	MACHINE SCREW PAN PHILLIPS, 5/16", 4-40	B&F Fastener Supply	PMSSS 440 0031 PH	1	Digi-Key	H704-ND			
39	H11	Washer, Split Lock, #4	Keystone	4693	1	Digi-Key	4693K-ND	Mouser	534-4693	
40	H12	Nut, Hex, 1/4" Thick, #4-40	B&F Fastener Supply	HNSS440	1	Digi-Key	H724-ND			
41	H13	MACHINE SCREW PAN PHILLIPS, 5/16", 4-40	B&F Fastener Supply	PMSSS 440 0031 PH	1	Digi-Key	H704-ND			
42	H14	Washer, Split Lock, #4	Keystone	4693	1	Digi-Key	4693K-ND	Mouser	534-4693	
43	H15	Nut, Hex, 1/4" Thick, #4-40	B&F Fastener Supply	HNSS440	1	Digi-Key	H724-ND			
44	HS1	BOARD LEVEL HEATSINK .375" TO-220	Aavid Thermalloy	7173DG	1	Digi-Key	HS415-ND			
45	HS2	BOARD LEVEL HEATSINK .375" TO-220	Aavid Thermalloy	7173DG	1	Digi-Key	HS415-ND			
46	J1	AC Receptacle, 2.5A, R/A, TH	Qualtek Electronics Corporation	770W-X2/10	1	Digi-Key	Q273-ND	Mouser	562-770W-X2/10	
47	J2	Terminal Block, 2x1, 5.08mm, TH	FCI	20020110-H021A01LF	1	Digi-Key	609-3907-ND	Mouser	649-220110-H021A01LF	
48	J3	TERM BLOCK PLUG 2POS 5.08MM	FCI	20020006-H021B01LF	1	Digi-Key	609-3885-ND	Mouser	649-220006-H021B01LF	
49	J4	Connector, SMB, Vertical RCP 0-4GHz, 50 ohm, TH	Emerson Network Power	131-3701-261	1	Digi-Key	J613-ND	Mouser	530-131-3701-261	
50	JMP1	RES, 0 ohm, 5%, 0.25W, 1206	Vishay-Dale	CRCW12060000Z0EA	1	Digi-Key	541-0.0ECT-ND	Mouser	71-CRCW1206-0-E3	
51	L1	Inductor, Toroid, 4.5mH, A, 0.05 ohm, TH	Renco Electronics	RLTI-1099	1					

52	L2	Inductor, Toroid, 47.7uH, A, 0.04 ohm, TH	Renco Electronics	RLTI-1098	1				
53	LED1	LED, Green, TH	Everlight	HLMP1523	1	Digi-Key	HLMP1523EL-ND	Mouser	638-HLMP1523
54	Q1	MOSFET, N-CH, 600V, 11A, TO-220 FullPAK	ST Microelectronics	STF13NM60ND	1	Digi-Key	497-13865-5-ND	Mouser	511-STF13NM60ND
55	R1	RES, 4.70 ohm, 1%, 0.125W, 0805	Panasonic	ERJ-6RFQ4R7V	1	Digi-Key	P4.7DCT-ND	Mouser	667-ERJ-6RFQ4R7V
56	R2	RES, 100k ohm, 1%, 0.25W, 1206	Yageo America	RC1206FR-07100KL	1	Digi-Key	311-100KFRCT-ND	Mouser	603-RC1206FR-07100KL
57	R3	RES, 100k ohm, 1%, 0.25W, 1206	Yageo America	RC1206FR-07100KL	1	Digi-Key	311-100KFRCT-ND	Mouser	603-RC1206FR-07100KL
58	R4	RES, 100 ohm, 1%, 0.1W, 0603	Vishay-Dale	CRCW0603100RFKEA	1	Digi-Key	541-100HCT-ND	Mouser	71-CRCW0603-100-E3
59	R5	RES, 1.00k ohm, 1%, 0.1W, 0603	Vishay-Dale	CRCW06031K00FKEA	1	Digi-Key	541-1.00KHCT-ND	Mouser	71-CRCW0603-1.0K-E3
60	R6	RES, 0 ohm, 5%, 0.1W, 0603	Vishay-Dale	CRCW0603000Z0EA	1	Digi-Key	541-0.0GCT-ND	Mouser	71-CRCW0603-0-E3
61	R7	RES, 22.6k ohm, 1%, 0.25W, 1206	Vishay-Dale	CRCW120622K6FKEA	1	Digi-Key	541-22.6KFCT-ND	Mouser	71-CRCW1206-22.6K-E3
62	R8	RES, 39k ohm, 5%, 0.25W, 1206	Vishay-Dale	CRCW120639K0JNEA	1	Digi-Key	541-39KECT-ND	Farnell	1540024
63	R9	RES, 180k ohm, 1%, 0.1W, 0603	Yageo America	RC0603FR-07180KL	1	Digi-Key	311-180KHRCT-ND	Mouser	603-RC0603FR-07180KL
64	R10	RES, 3.90k ohm, 1%, 0.1W, 0603	Yageo America	RC0603FR-073K9L	1	Digi-Key	311-3.90KHRCT-ND	Mouser	603-RC0603FR-073K9L
65	R11	RES, 47.0 ohm, 1%, 0.25W, 1206	Yageo America	RC1206FR-0747RLL	1	Digi-Key	311-47.0FRCT-ND	Mouser	603-RC1206FR-0747RLL
66	R13	RES, 4.7 ohm, 5%, 0.25W, 1206	Vishay-Dale	CRCW12064R70JNEA	1	Digi-Key	541-4.7ECT-ND	Mouser	71-CRCW1206J-4.7-E3
67	R15	RES, 100k ohm, 1%, 0.1W, 0603	Vishay-Dale	CRCW0603100KFKEA	1	Digi-Key	541-100KHCT-ND	Mouser	71-CRCW0603-100K-E3
68	R16	RES, 0.2 ohm, 1%, 2W, 2512	Stackpole Electronics Inc	CSRN2512FKR200	1	Digi-Key	CSRN2512FKR200CT-ND		
69	R18	RES, 12.0k ohm, 1%, 0.25W, 1206	Yageo America	RC1206FR-0712KL	1	Digi-Key	311-12.0KFRCT-ND	Mouser	603-RC1206FR-0712KL
70	R20	RES, 150k ohm, 1%, 0.1W, 0603	Vishay-Dale	CRCW0603150KFKEA	1	Digi-Key	541-150KHCT-ND	Mouser	71-CRCW0603-150K-E3
71	R21	RES, 470k ohm, 1%, 0.1W, 0603	Yageo America	RC0603FR-07470KL	1	Digi-Key	311-470KHRCT-ND	Mouser	603-RC0603FR-07470KL
72	R22	RES, 150k ohm, 1%, 0.1W, 0603	Vishay-Dale	CRCW0603150KFKEA	1	Digi-Key	541-150KHCT-ND	Mouser	71-CRCW0603-150K-E3
73	R23	RES, 47.0k ohm, 1%, 0.1W, 0603	Yageo America	RC0603FR-0747KL	1	Digi-Key	311-47.0KHRCT-ND	Mouser	603-RC0603FR-0747KL
74	R24	RES, 10.5k ohm, 1%, 0.1W, 0603	Yageo America	RC0603FR-0710K5L	1	Digi-Key	311-10.5KHRCT-ND	Mouser	603-RC0603FR-0710K5L
75	R25	RES, 10.0k ohm, 1%, 0.25W, 1206	Vishay-Dale	CRCW120610K0FKEA	1	Digi-Key	541-10.0KFCT-ND	Mouser	71-CRCW1206-10K-E3
76	RT1	Thermistor NTC, 470k ohm, 5%, Disc, 5.5x5mm	EPCOS Inc	B57164K474J	1	Digi-Key	495-2084-ND	Mouser	871-B57164K474J
77	T1	RM10-5pin Custom Transformer		Custom	1				
78	TP1	Test Point, Compact, Red, TH	Keystone	5005	1	Digi-Key	5005K-ND		
79	TP2	Test Point, Compact, White, TH	Keystone	5007	1	Digi-Key	5007K-ND		
80	TP3	Test Point, Compact, Black, TH	Keystone	5006	1	Digi-Key	5006K-ND		
81	TP4	Test Point, Compact, Red, TH	Keystone	5005	1	Digi-Key	5005K-ND		
82	TP5	Test Point, Compact, Black, TH	Keystone	5006	1	Digi-Key	5006K-ND		
83	TP6	Test Point, Compact, Red, TH	Keystone	5005	1	Digi-Key	5005K-ND		
84	TP7	Test Point, Compact, Black, TH	Keystone	5006	1	Digi-Key	5006K-ND		
85	TP8	Test Point, Compact, Black, TH	Keystone	5006	1	Digi-Key	5006K-ND		
86	TP10	Test Point, Compact, Red, TH	Keystone	5005	1	Digi-Key	5005K-ND		
87	U1	Green-Mode Flyback Controller, D0007A	Texas Instruments	UCC28630D	1				
88	U2	Transistor Output Optocoupler	Lite-On	LTV-357T	1			Mouser	859-LTV-357T
89	U3	IC VREF SHUNT PREC ADJ	Texas Instruments	TLVH432ACDBZR	1	Digi-Key	296-17976-1-ND		
90	U4	IC SNGL DIFF COMPARATOR	Texas Instruments	TL331IDBVT	1	Digi-Key	296-26708-1-ND		
91	V1	Varistor, 430V, 4.5KA, TH	EPCOS Inc	B72214S0271K101	1	Digi-Key	495-1412-ND	Mouser	871-B72214S0271K101
92	C8	CAP, CERM, 2700pF, 250V, +/-5%, C0G/NP0, 0805	TDK	C2012C0G2E272J	0	Digi-Key	445-2328-1-ND		
93	C10	CAP, CERM, 0.082uF, 16V, +/-10%, X7R, 0603	AVX	0603YC823KAT2A	0	Digi-Key	478-1238-1-ND	Mouser	581-0603YC823KAT2A
94	D10	Diode, Zener, 100V, 310mW, SOD-323F	NXP Semiconductor	BZX100A, 115	0	Digi-Key	568-6278-1-ND	Mouser	771-BZX100A115
95	R12	RES, 1.00 ohm, 1%, 0.25W, 1206	Vishay-Dale	CRCW12061R00FKEA	0	Mouser	71-CRCW1206-1-E3	Farnell	1653087
96	R14		Vishay / Dale		0				
97	R17	RES, 1.00k ohm, 1%, 0.25W, 1206	Vishay-Dale	CRCW12061K00FKEA	0	Digi-Key	541-1.00KFCT-ND	Mouser	71-CRCW1206-1.0K-E3
98	R19		Vishay / Dale		0				

IMPORTANT NOTICE FOR TI REFERENCE DESIGNS

Texas Instruments Incorporated ("TI") reference designs are solely intended to assist designers ("Buyers") who are developing systems that incorporate TI semiconductor products (also referred to herein as "components"). Buyer understands and agrees that Buyer remains responsible for using its independent analysis, evaluation and judgment in designing Buyer's systems and products.

TI reference designs have been created using standard laboratory conditions and engineering practices. **TI has not conducted any testing other than that specifically described in the published documentation for a particular reference design.** TI may make corrections, enhancements, improvements and other changes to its reference designs.

Buyers are authorized to use TI reference designs with the TI component(s) identified in each particular reference design and to modify the reference design in the development of their end products. HOWEVER, NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER TI INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY THIRD PARTY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT, IS GRANTED HEREIN, including but not limited to any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services, or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

TI REFERENCE DESIGNS ARE PROVIDED "AS IS". TI MAKES NO WARRANTIES OR REPRESENTATIONS WITH REGARD TO THE REFERENCE DESIGNS OR USE OF THE REFERENCE DESIGNS, EXPRESS, IMPLIED OR STATUTORY, INCLUDING ACCURACY OR COMPLETENESS. TI DISCLAIMS ANY WARRANTY OF TITLE AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, QUIET ENJOYMENT, QUIET POSSESSION, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS WITH REGARD TO TI REFERENCE DESIGNS OR USE THEREOF. TI SHALL NOT BE LIABLE FOR AND SHALL NOT DEFEND OR INDEMNIFY BUYERS AGAINST ANY THIRD PARTY INFRINGEMENT CLAIM THAT RELATES TO OR IS BASED ON A COMBINATION OF COMPONENTS PROVIDED IN A TI REFERENCE DESIGN. IN NO EVENT SHALL TI BE LIABLE FOR ANY ACTUAL, SPECIAL, INCIDENTAL, CONSEQUENTIAL OR INDIRECT DAMAGES, HOWEVER CAUSED, ON ANY THEORY OF LIABILITY AND WHETHER OR NOT TI HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES, ARISING IN ANY WAY OUT OF TI REFERENCE DESIGNS OR BUYER'S USE OF TI REFERENCE DESIGNS.

TI reserves the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques for TI components are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

Reproduction of significant portions of TI information in TI data books, data sheets or reference designs is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards that anticipate dangerous failures, monitor failures and their consequences, lessen the likelihood of dangerous failures and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in Buyer's safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed an agreement specifically governing such use.

Only those TI components that TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components that have **not** been so designated is solely at Buyer's risk, and Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.