

**TIDA-01529 REV B Bill of Materials**

Item #	Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
1	IPCB	1		TIDA-01529	Any	Printed Circuit Board	
2	C1, C6, C34	3	1uF	UMK107AB7105KA-T	Taiyo Yuden	CAP, CERM, 1 uF, 50 V, +/- 10%, X7R, 0603	0603
3	C2, C3, C4, C5	4	0.1uF	C0603X104K3RACTU	Kemet	CAP, CERM, 0.1 uF, 25 V, +/- 10%, X7R, 0603	0603
4	C9, C10, C11, C12, C13, C14, C15, C16, C21, C22, C23, C24, C26, C28, C29, C30, C31, C32, C33	19	0.1uF	GRM155R71C104KA88D	MuRata	CAP, CERM, 0.1 uF, 16 V, +/- 10%, X7R, 0402	0402
5	C17, C18	2	47pF	GRM1555C1E470JA01D	MuRata	CAP, CERM, 47 pF, 25 V, +/- 5%, COG/NP0, 0402	0402
6	C19	1	100pF	CGA2B2COG1H101J050BA	TDK	CAP, CERM, 100 pF, 50 V, +/- 5%, COG/NP0, AEC-Q200 Grade 1, 0402	0402
7	C20	1	1000pF	GRM1555C1H102JA01D	MuRata	CAP, CERM, 1000 pF, 50 V, +/- 5%, COG/NP0, 0402	0402
8	C25	1	22uF	C2012X5R1C226K125AC	TDK	CAP, CERM, 22 uF, 16 V, +/- 10%, X5R, 0805	0805
9	C27	1	0.01uF	GRM155R70J103KA01D	MuRata	CAP, CERM, 0.01 uF, 6.3 V, +/- 10%, X7R, 0402	0402
10	D1, D2	2	Red	LTST-C170KRKT	Lite-On	LED, Red, SMD	Red 0805 LED
11	D3, D4	2	Yellow	LTST-C170KSMT	Lite-On	LED, Yellow, SMD	0805 LED
12	H1, H2, H3, H4	4		NY PMS 440 0025 PH	B&F Fastener Supply	Machine Screw, Round, #4-40 x 1/4, Nylon, Phillips panhead	Screw
13	H5, H6, H7, H8	4		1902C	Keystone		Standoff
14	J1	1		972	Keystone	RCA Jack, Black, R/A, TH	RCA Jack, Black, R/A, TH
15	J2, J6, J7, J8, J9, J10, J11, J12, J22, J23, J24, J25, J26, J27	14		PBC03SAAN	Sullins Connector Solutions	Header, 100mil, 3x1, Gold, TH	PBC03SAAN
16	J3	1		971	Keystone	RCA Jack, Red, R/A, TH	PC Mount Phono Jack-Red, TH
17	J4, J5	2		ED555/2DS	On-Shore Technology	Terminal Block, 3.5mm Pitch, 2x1, TH	7.0x8.2x6.5mm
18	J13, J14, J15, J16, J17, J18, J20, J21, J28	9		PBC02SAAN	Sullins Connector Solutions	Header, 100mil, 2x1, Gold, TH	Sullins 100mil, 1x2, 230 mil above insulator
19	J19	1		DX4R205JJAR1800	JAE Electronics	Connector, Receptacle, Micro-USB Type AB, R/A, Bottom Mount SMT	Connector, USB Micro AB
20	L1, L2	2	220 ohm	MPZ1608S221A	TDK	Ferrite Bead, 220 ohm @ 100 MHz, 2.2 A, 0603	0603
21	Q1, Q2, Q3, Q5	4	40 V	MMBT2222A	Fairchild Semiconductor	Transistor, NPN, 40 V, 0.15 A, SOT-23	SOT-23
22	Q4	1	-60V	BSH201,215	NXP Semiconductor	MOSFET, P-CH, -60 V, -0.3 A, SOT-23	SOT-23
23	R1, R2	2	0	RC1206JR-070RL	Yageo America	RES, 0, 5%, 0.25 W, 1206	1206
24	R3, R4, R8, R11, R16, R26, R28, R29, R30, R37, R38	11	10.0k	ERJ-2RKF1002X	Panasonic	RES, 10.0 k, 1%, 0.1 W, 0402	0402
25	R5, R10	2	820	RC0402FR-07820RL	Yageo America	RES, 820, 1%, 0.063 W, 0402	0402
26	R6	1	200k	ERJ-2RKF2003X	Panasonic	RES, 200 k, 1%, 0.1 W, 0402	0402
27	R7	1	16.9k	ERA-2AEB1692X	Panasonic	RES, 16.9 k, 0.1%, 0.063 W, 0402	0402
28	R9	1	9.09k	RC0603FR-079K09L	Yageo America	RES, 9.09 k, 1%, 0.1 W, 0603	0603
29	R12, R27	2	100k	RC0402FR-07100KL	Yageo America	RES, 100 k, 1%, 0.0625 W, 0402	0402
30	R13	1	0	RC0402JR-070RL	Yageo America	RES, 0, 5%, 0.063 W, 0402	0402
31	R14, R15, R33, R39, R42	5	2.00k	ERJ-2RKF2001X	Panasonic	RES, 2.00 k, 1%, 0.1 W, AEC-Q200 Grade 0, 0402	0402
32	R17	1	15.0k	ERA-2AEB153X	Panasonic	RES, 15.0 k, .1%, .063 W, AEC-Q200 Grade 0, 0402	0402
33	R18	1	1.50k	ERA-2AEB152X	Panasonic	RES, 1.50 k, 0.1%, 0.063 W, AEC-Q200 Grade 0, 0402	0402
34	R19, R22, R23, R24	4	49.9	RC0402FR-0749R9L	Yageo America	RES, 49.9, 1%, 0.063 W, 0402	0402
35	R20, R21	2	27.4	RC0603FR-0727R4L	Yageo America	RES, 27.4, 1%, 0.1 W, 0603	0603
36	R25	1	3.09k	ERA-2AEB3091X	Panasonic	RES, 3.09 k, 0.1%, 0.062 W, AEC-Q200 Grade 0, 0402	0402
37	R31, R32	2	649	RC0603FR-07649RL	Yageo America	RES, 649, 1%, 0.1 W, 0603	0603
38	R34, R35, R40, R41	4	20k	ERJ-2GEJ203X	Panasonic	RES, 20 k, 5%, 0.1 W, AEC-Q200 Grade 0, 0402	0402
39	R36	1	1.00k	ERJ-2RKF1001X	Panasonic	RES, 1.00 k, 1%, 0.1 W, 0402	0402
40	S1, S2, S3, S4	4		TL1015AF160QG	E-Switch	Switch, Tactile, SPST-NO, 0.05A, 12V, SMT	Switch, 4.4x2x2.9 mm
41	SH-J1, SH-J2, SH-J3, SH-J4, SH-J5, SH-J6, SH-J7, SH-J8, SH-J9, SH-J10, SH-J11, SH-J12, SH-J13, SH-J14, SH-J15	15	1x2	SNT-100-BK-G	Samtec	Shunt, 100mil, Gold plated, Black	Shunt
42	U1	1		TAS2505TRGERQ1	Texas Instruments	2.6-W Digital/Analog Input Automotive Class-D Speaker Amplifier With Audio Processing, RGE0024K (VOFN-24)	RGE0024K
43	U2	1		LM2903QDGKRO1	Texas Instruments	Dual Differential Comparators, DGK0008A (VSSOP-8)	DGK0008A
44	U3	1		24LC512-I/ST	Microchip	EEPROM, 512KBIT, 400KHZ, 8TSSOP	TSSOP-8
45	U4	1		TCA9406DCUR	Texas Instruments	TCA9406 Dual Bidirectional 1-MHz I2C-BUS and SMBus Voltage Level-Translator, 1.65 to 3.6 V, -40 to 85 degC, 8-pin US8 (DCU), Green (RoHS & no Sb/Br)	DCU0008A
46	U5	1		SN74LVC1G126DCKR	Texas Instruments	Single Bus Buffer Gate With 3-State Outputs, DCK0005A, LARGE T&R	DCK0005A
47	U6	1		TAS1020BPFBR	Texas Instruments	USB Streaming Controller, NRND, PFB0048A (TQFP-48)	PFB0048A
48	U7	1		TPS73633DBVR	Texas Instruments	Single Output Low Noise LDO, 400 mA, Fixed 3.3 V Output, 1.7 to 5.5 V Input, with Reverse Current Protection, 5-pin SOT-23 (DBV), -40 to 85 degC, Green (RoHS & no Sb/Br)	DBV0005A
49	U8, U9	2		SN74AVC4774RSVR	Texas Instruments	4-Bit Dual-Supply Bus Transceiver With Configurable Voltage-Level Shifting and 3-State Outputs, RSV0016A (UQFN-16)	RSV0016A
50	Y1	1		625L31006M00000	CTS Electrocomponents	Oscillator, 6 MHz, 3.3V, SMD	2.5x1x2.5mm
51	C7, C8	0	1uF	GRM319R71C105KAA3D	MuRata	CAP, CERM, 1 uF, 16 V, +/- 10%, X7R, 1206	1206
52	FID1, FID2, FID3, FID4, FID5, FID6	0		N/A	N/A	Fiducial mark. There is nothing to buy or mount.	N/A

## IMPORTANT NOTICE FOR TI DESIGN INFORMATION AND RESOURCES

Texas Instruments Incorporated ("TI") technical, application or other design advice, services or information, including, but not limited to, reference designs and materials relating to evaluation modules, (collectively, "TI Resources") are intended to assist designers who are developing applications that incorporate TI products; by downloading, accessing or using any particular TI Resource in any way, you (individually or, if you are acting on behalf of a company, your company) agree to use it solely for this purpose and subject to the terms of this Notice.

TI's provision of TI Resources does not expand or otherwise alter TI's applicable published warranties or warranty disclaimers for TI products, and no additional obligations or liabilities arise from TI providing such TI Resources. TI reserves the right to make corrections, enhancements, improvements and other changes to its TI Resources.

You understand and agree that you remain responsible for using your independent analysis, evaluation and judgment in designing your applications and that you have full and exclusive responsibility to assure the safety of your applications and compliance of your applications (and of all TI products used in or for your applications) with all applicable regulations, laws and other applicable requirements. You represent that, with respect to your applications, you have all the necessary expertise to create and implement safeguards that (1) anticipate dangerous consequences of failures, (2) monitor failures and their consequences, and (3) lessen the likelihood of failures that might cause harm and take appropriate actions. You agree that prior to using or distributing any applications that include TI products, you will thoroughly test such applications and the functionality of such TI products as used in such applications. TI has not conducted any testing other than that specifically described in the published documentation for a particular TI Resource.

You are authorized to use, copy and modify any individual TI Resource only in connection with the development of applications that include the TI product(s) identified in such TI Resource. NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER TI INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT OF TI OR ANY THIRD PARTY IS GRANTED HEREIN, including but not limited to any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information regarding or referencing third-party products or services does not constitute a license to use such products or services, or a warranty or endorsement thereof. Use of TI Resources may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

TI RESOURCES ARE PROVIDED "AS IS" AND WITH ALL FAULTS. TI DISCLAIMS ALL OTHER WARRANTIES OR REPRESENTATIONS, EXPRESS OR IMPLIED, REGARDING TI RESOURCES OR USE THEREOF, INCLUDING BUT NOT LIMITED TO ACCURACY OR COMPLETENESS, TITLE, ANY EPIDEMIC FAILURE WARRANTY AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

TI SHALL NOT BE LIABLE FOR AND SHALL NOT DEFEND OR INDEMNIFY YOU AGAINST ANY CLAIM, INCLUDING BUT NOT LIMITED TO ANY INFRINGEMENT CLAIM THAT RELATES TO OR IS BASED ON ANY COMBINATION OF PRODUCTS EVEN IF DESCRIBED IN TI RESOURCES OR OTHERWISE. IN NO EVENT SHALL TI BE LIABLE FOR ANY ACTUAL, DIRECT, SPECIAL, COLLATERAL, INDIRECT, PUNITIVE, INCIDENTAL, CONSEQUENTIAL OR EXEMPLARY DAMAGES IN CONNECTION WITH OR ARISING OUT OF TI RESOURCES OR USE THEREOF, AND REGARDLESS OF WHETHER TI HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

You agree to fully indemnify TI and its representatives against any damages, costs, losses, and/or liabilities arising out of your non-compliance with the terms and provisions of this Notice.

This Notice applies to TI Resources. Additional terms apply to the use and purchase of certain types of materials, TI products and services. These include; without limitation, TI's standard terms for semiconductor products (<http://www.ti.com/sc/docs/stdterms.htm>), [evaluation modules](#), and [samples](http://www.ti.com/sc/docs/sampterm.htm) (<http://www.ti.com/sc/docs/sampterm.htm>).

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265  
Copyright © 2018, Texas Instruments Incorporated