Filename:
 ProFB4C.tmp

 Variant:
 002

 Generated:
 7/18/2017 12:38:17 PM

 TID #:
 TIDA-00461



TIDA-00461 REV E1 Bill of Materials

Item #	Designator	Quantity	Value	PartNumber	Manufacturer	Description	PackageReference
1	C1, C4	2	150pF	GRM1555C1H151JA01D	MuRata	CAP, CERM, 150 pF, 50 V, +/- 5%, C0G/NP0, 0402	0402
2	C2	1	1uF	CGA4J3X7S2A105K125AB	TDK	CAP, CERM, 1 uF, 100 V, +/- 10%, X7S, AEC-Q200 Grade 1, 0805	0805
3	C3, C6	2	1uF	GRM155R61A105KE15D	MuRata	CAP, CERM, 1 uF, 10 V, +/- 10%, X5R, 0402	0402
4	C5, C7	2	0.1uF	GRM155R71C104JA88D	MuRata	CAP, CERM, 0.1 uF, 16 V, +/- 5%, X7R, 0402	0402
5	C9, C10	2	10pF	GRM1555C1H100RA01D	MuRata	CAP, CERM, 10 pF, 50 V, +/- 4%, C0G/NP0, 0402	0402
6	D2	1	Rab	SMLP36RGB2W3	Rohm	LED, Rab, SMD	1.5x1mm
7	D3, D4, D5	3	Green	150060VS75000	Wurth Elektronik	LED, Green, SMD	LED 0603
8	FID1, FID2, FID3	3		N/A	N/A	Fiducial mark. There is nothing to buy or mount.	N/A
9	H1, H2, H3, H4	4		NY PMS 440 0025 PH	B&F Fastener Supply	Machine Screw, Round, #4-40 x 1/4, Nylon, Philips panhead	Screw
10	H5, H6, H7, H8	4		1902C	Keystone	Standoff, Hex, 0.5"L #4-40 Nylon	Standoff
11	H9	1		1803578	Phoenix Contact	Terminal Block Plug, 3.81mm, 2x1, Green	
12	J1	1				M12 Socket, Backmounting, 4Pos, Gold, R/A, TH	
13	J2, J13	2		61300311121	Wurth Elektronik	Header, 2.54 mm, 3x1, Gold, TH	Header, 2.54mm, 3x1, TH
14	J3, J4	2		61300211121	Wurth Elektronik	Header, 2.54 mm, 2x1, Gold, TH	Header, 2.54mm, 2x1, TH
15	J11, J12	2		61301011121	Wurth Elektronik	Header, 2.54mm, 10x1, Gold, TH	Header, 2.54mm,
15	011, 012	2		01001011121	Warth Electronic		10x1, TH
16	J14	1		612 014 217 21	Wurth Elektronik	Header (Shrouded), 2.54 mm, 7x2, Gold, R/A, TH	Header, 2.54 mm,
10	514	'		012 014 217 21			7x2, R/A, TH
17	J15	1		61300611121	Wurth Elektronik	Header, 2.54 mm, 6x1, Gold, TH	Header, 2.54mm,
17	515	'		01300011121			6x1, TH
18	LBL1	1		THT-14-423-10	Brady	Thermal Transfer Printable Labels, 0.650" W x 0.200" H - 10,000 per roll	PCB Label 0.650 x
							0.200 inch
19	R1, R2	2	10.0k	CRCW020110K0FKED	Vishay-Dale	RES, 10.0 k, 1%, 0.05 W, 0201	0201
20	R3	1	0	CRCW04020000Z0ED	Vishay-Dale	RES, 0, 5%, 0.063 W, 0402	0402
21	R7, R8	2	140	CRCW0402140RFKED	Vishay-Dale	RES, 140, 1%, 0.063 W, 0402	0402
22	R9	1	499	CRCW0402499RFKED	Vishay-Dale	RES, 499, 1%, 0.063 W, 0402	0402
23	R11, R13, R14	3	68.1	CRCW040268R1FKED	Vishay-Dale	RES, 68.1, 1%, 0.063 W, 0402	0402
24	R12	1	47.5k	CRCW060347K5FKEA	Vishay-Dale	RES, 47.5 k, 1%, 0.1 W, 0603	0603
25	S1, S2	2		434121025816	Wurth Elektronik	Switch, Tactile, SPST, 12 V, SMD	SMD, 6x3.9mm
26	SH-J3, SH-J13	2		60900213421	Wurth Elektronik	Shunt, 2.54mm, Gold, Black	Shunt, 2.54mm, Black
27	U1	1		TIOL111	Texas Instruments	IO-Link Device Transceiver with Integrated Surge Protection, TIOL111 (WSON-10)	TIOL111
28	U2	1		MSP430FR5969IRGZR	Texas Instruments	MSP430FR5969 16 MHz Ultra-Low-Power Microcontroller featuring 64	RGZ0048B
						KB FRAM, 2 KB SRAM, 40 IO, RGZ0048B (VQFN-48)	
29	Y1	1		MS3V-T1R 32.768KHZ 7.0 PF	Micro Crystal AG	Crystal, 32.768 KHz, 7pF, SMD	1.4x1.4x5.0mm SMD
30	C8	0	100pF	GRM1885C1H101JA01D	MuRata	CAP, CERM, 100 pF, 50 V, +/- 5%, C0G/NP0, 0603	0603
31	C11	0	1000pF	885012205061	Wurth Elektronik	CAP, CERM, 1000 pF, 50 V, +/- 10%, X7R, 0402	0402
32	D1	0	600V	MURS160-13-F	Diodes Inc.	Diode, Ultrafast, 600 V, 1 A, SMB	SMB
33	J5	0		1803277	Phoenix Contact	Terminal Block, 2x1, 3.81mm, R/A, TH	Connector, 2 pos.
							3.8mm RA
34	J7, J8, J9, J10	0		61300211121	Wurth Elektronik	Header, 2.54 mm, 2x1, Gold, TH	Header, 2.54mm, 2x1, TH
35	Q1	0	60V	DMN61D8L-7	Diodes Inc.	MOSFET, N-CH, 60 V, 0.47 A, AEC-Q101, SOT-23	SOT-23
36	R4	0	0	CRCW06030000Z0EA	Vishay-Dale	RES, 0, 5%, 0.1 W, 0603	0603
	R5	0	100k	CRCW0603100KFKEA	Vishay-Dale	RES, 100 k, 1%, 0.1 W, 0603	0603
38	R6	0	1.00k	CRCW06031K00FKEA	Vishay-Dale	RES, 1.00 k, 1%, 0.1 W, 0603	0603
39	R10	0	1.00	CRCW25121R00FNEG	Vishay-Dale	RES, 1.00, 1%, 1 W, AEC-Q200 Grade 0, 2512	2512
40	SH-J7, SH-J8, SH-	0		60900213421	Wurth Elektronik	Shunt, 2.54mm, Gold, Black	Shunt, 2.54mm,
	J9						Black

IMPORTANT NOTICE FOR TI DESIGN INFORMATION AND RESOURCES

Texas Instruments Incorporated ('TI") technical, application or other design advice, services or information, including, but not limited to, reference designs and materials relating to evaluation modules, (collectively, "TI Resources") are intended to assist designers who are developing applications that incorporate TI products; by downloading, accessing or using any particular TI Resource in any way, you (individually or, if you are acting on behalf of a company, your company) agree to use it solely for this purpose and subject to the terms of this Notice.

TI's provision of TI Resources does not expand or otherwise alter TI's applicable published warranties or warranty disclaimers for TI products, and no additional obligations or liabilities arise from TI providing such TI Resources. TI reserves the right to make corrections, enhancements, improvements and other changes to its TI Resources.

You understand and agree that you remain responsible for using your independent analysis, evaluation and judgment in designing your applications and that you have full and exclusive responsibility to assure the safety of your applications and compliance of your applications (and of all TI products used in or for your applications) with all applicable regulations, laws and other applicable requirements. You represent that, with respect to your applications, you have all the necessary expertise to create and implement safeguards that (1) anticipate dangerous consequences of failures, (2) monitor failures and their consequences, and (3) lessen the likelihood of failures that might cause harm and take appropriate actions. You agree that prior to using or distributing any applications. TI has not conducted any testing other than that specifically described in the published documentation for a particular TI Resource.

You are authorized to use, copy and modify any individual TI Resource only in connection with the development of applications that include the TI product(s) identified in such TI Resource. NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER TI INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT OF TI OR ANY THIRD PARTY IS GRANTED HEREIN, including but not limited to any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information regarding or referencing third-party products or services does not constitute a license to use such products or services, or a warranty or endorsement thereof. Use of TI Resources may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

TI RESOURCES ARE PROVIDED "AS IS" AND WITH ALL FAULTS. TI DISCLAIMS ALL OTHER WARRANTIES OR REPRESENTATIONS, EXPRESS OR IMPLIED, REGARDING TI RESOURCES OR USE THEREOF, INCLUDING BUT NOT LIMITED TO ACCURACY OR COMPLETENESS, TITLE, ANY EPIDEMIC FAILURE WARRANTY AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

TI SHALL NOT BE LIABLE FOR AND SHALL NOT DEFEND OR INDEMNIFY YOU AGAINST ANY CLAIM, INCLUDING BUT NOT LIMITED TO ANY INFRINGEMENT CLAIM THAT RELATES TO OR IS BASED ON ANY COMBINATION OF PRODUCTS EVEN IF DESCRIBED IN TI RESOURCES OR OTHERWISE. IN NO EVENT SHALL TI BE LIABLE FOR ANY ACTUAL, DIRECT, SPECIAL, COLLATERAL, INDIRECT, PUNITIVE, INCIDENTAL, CONSEQUENTIAL OR EXEMPLARY DAMAGES IN CONNECTION WITH OR ARISING OUT OF TI RESOURCES OR USE THEREOF, AND REGARDLESS OF WHETHER TI HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

You agree to fully indemnify TI and its representatives against any damages, costs, losses, and/or liabilities arising out of your noncompliance with the terms and provisions of this Notice.

This Notice applies to TI Resources. Additional terms apply to the use and purchase of certain types of materials, TI products and services. These include; without limitation, TI's standard terms for semiconductor products http://www.ti.com/sc/docs/stdterms.htm), evaluation modules, and samples (http://www.ti.com/sc/docs/stdterms.htm), evaluation

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265 Copyright © 2017, Texas Instruments Incorporated